Gamewell FCI FIRE CONTROL INSTRUMENTS by Honeywell

Technical Bulletin

Date: January 12, 2015 No. T15.1

To: All Gamewell-FCI Distributors

Updated Software Compatibility Charts

Making the correct choices concerning E3 firmware, FocalPoint® and CAMWorks!

Our technical department has developed a series of compatibility charts to visually assist in making the proper selection of the firmware that is compatible to the version of CamWorks needed for system upgrades.

E3 Firmware Compatibility Chart 1

Firmware Compatibility Chart 1 ILI-MB/S, ILI95-MB/S and NGA

Firmware Compatibility Document		ILI-MB / S									ILI95-MB / S								NGA						
		v 1.04.001	v1.05.002	v 1.07.011	v2.04.088	v2.06.003	v2.07.061	v3.00.116	v3.01.051	v3.02.285	v1.09.001	v2.00.002	v2.02.011	v2.04.088	v2.06.003	v2.07.061	v3.00.116	v3.01.051	v3.02.285	v2.00.691	v2.10.014	v2.20.024	v2.30.003	v2.31.001	v3.00.240	v3.10.142
ILI-MB / S	v 1.04.001										X									X						
	v1.05.002											X									X					
	v 1.07.011												X								X					
	v2.04.088													X								X				
	v2.06.003														X								X			
	v2.07.061															X								X		
	v3.00.116																X								X	
	v3.01.051																	X							X	
	v3.02.285																		X							X
ILI95-MB / S	v1.09.001	X																		X						
	v2.00.002		X																		X					
	v2.02.011			X																	X					
	v2.04.086				X																	X				
	v2.06.003					X																	X			
	v2.07.061						X																	X		
	v3.00.116							X																	X	
	v3.01.051								X																X	
	v3.02.285									X																X
NGA	v2.00.691	X									X															
	v2.10.014		X	X								X	X													
	v2.20.024				X									X												
	v2.30.003					X									X											
	v2.31.001						X									X										
	v3.00.240							X	X								X	X								
	v3.10.142									X									X							

X*	Downgrades the ILI to 7100 format
X**	Only upgradeable when RPT is connected to the S3 panel

Firmware Compatibility Chart 2 ANX, 7100, S3, LCD-SLP and RPT-E3

	Firmware Compatibility Document	ANX					7100					S3				LCD-SLP				RPT-E3	
		v1.00.049	v1.10.005	v1.20.070	v1.30.079		v6.04.160	v7.01.001	v7.00.156	v7.02.024		v1.00.026	v1.01.019	v1.11.009		v1.00.112	v1.01.123	v1.02.001		v1.00.057	v1.01.001
ILI-MB/S	v 1.04.001						X*	X*	X*	X*										X	X**
	v1.05.002	X					X*	X*	X*	X*										X	X**
	v 1.07.011	X					X*	X*	X*	X*										X	X**
	v2.04.088	X					X*	X*	X*	X*										X	X**
	v2.06.003		X				X*	X*	X*	X*										X	X**
	v2.07.061		X				X*	X*	X*	X*										X	X**
	v3.00.116			X			X*	X*	X*	X*										X	X**
	v3.01.051			X					X*	X*		X	X			X	X			X	X**
	v3.02.285				X				X*	X*				X				X		X	X**
ILI05-MB/S	v1.09.001						N/A	N/A	N/A	N/A										X	X**
	v2.00.002	X					N/A	N/A	N/A	N/A										X	X**
	v2.02.011	X					N/A	N/A	N/A	N/A										X	X**
	v2.04.086	X					N/A	N/A	N/A	N/A										X	X**
	v2.06.003		X				N/A	N/A	N/A	N/A										X	X**
	v2.07.061		X				N/A	N/A	N/A	N/A										X	X**
	v3.00.116			X			N/A	N/A	N/A	N/A										X	X**
	v3.01.051			X			N/A	N/A	N/A	N/A		X	X			X	X			X	X**
	v3.02.285				X		N/A	N/A	N/A	N/A				X				X		X	X**
NGA	v2.00.691						X	X	X	X											
	v2.10.014	X					X	X	X	X											
	v2.20.024	X					X	X	X	X											
	v2.30.003		X				X	X	X	X											
	v2.31.001		X				X	X	X	X											
	v3.00.240			X			X	X	X	X		X	X			X	X				
	v3.10.142				X				X	X				x				x			

X*	Downgrades the ILI to 7100 format
X**	Only upgradeable when RPT is connected to the S3 panel

Firmware Compatibility Chart 3 ILI-MB/S, ILI95-MB/S and NGA

Firmware Compatibility Document		ILI-MB / S									ILI95-MB / S									NGA						
		v 1.04.001	v1.05.002	v 1.07.011	v2.04.088	v2.06.003	v2.07.061	v3.00.116	v3.01.051	v3.02.285	v1.09.001	v2.00.002	v2.02.011	v2.04.088	v2.06.003	v2.07.061	v3.00.116	v3.01.051	v3.02.285	v2.00.691	v2.10.014	v2.20.024	v2.30.003	v2.31.001	v3.00.240	v3.10.142
ANX	v1.00.049		X	X	X							X	X	X							X	X				
	v1.10.005					X	X								X	X							X	X		
	v1.20.070							X	X								X	X							X	
	v1.30.079									X									X							X
7100	v6.04.160	X*	X*	X*	X*	X*	X*	X*			N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	X	X	X	X	X	X	
	v7.00.156	X*	X*	X*	X*	X*	X*	X*			N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	X	X	X	X	X	X	
	v7.01.001	X*	X*	X*	X*	X*	X*	X*	X*		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	X	X	X	X	X	X	
	v7.02.024								X*	X*								N/A	N/A						X	X
S3	v1.00.026								X									X							X	
	v1.01.019								X									X							X	
	v1.11.009									X									X							X
LCD-SLP	v1.00.112																									
	v1.01.123																									
	v1.02.001									X									X							
RPT-E3	v1.00.057									X									X							
	v1.01.001									X**									X**							

X*	Downgrades the ILI to 7100 format
X**	Only upgradeable when RPT is connected to the S3 panel

Firmware Compatibility Chart 4 ANX, 7100, S3, LCD-SLP and RPT-E3

Firmware Compatibility Document		ANX					7100					S3				LCD-SLP				RPT-E3		
		v1.00.049	v1.10.005	v1.20.070	v1.30.079		v6.04.160	v7.01.001	v7.00.156	v7.02.024		v1.00.026	v1.01.019	v1.11.009		v1.00.112	v1.01.123	v1.02.001		v1.00.057	v1.01.001	
ANX	v1.00.049						N/A	N/A	N/A	N/A										X	X**	
	v1.10.005						N/A	N/A	N/A	N/A										X	X**	
	v1.20.070						N/A	N/A	N/A	N/A		X	X			X	X			X	X**	
	v1.30.079									N/A				X				X		X	X**	
7100	v6.04.160	N/A	N/A	N/A																		
	v7.00.156	N/A	N/A	N/A																		
	v7.01.001	N/A	N/A	N/A								X	X	X		X	X	X				
	v7.02.024			N/A	N/A							X	X	X		X	X	X				
S3	v1.00.026			X					X	X						X	X			X	X**	
	v1.01.019			X					X	X						X	X			X	X**	
	v1.11.009				X					X								X				
LCD-SLP	v1.00.112											X	X									
	v1.01.123											X	X									
	v1.02.001													X								
RPT-E3	v1.00.057											X	X	X								
	v1.01.001											X**	X**	X**								

X*	Downgrades the ILI to 7100 format
X**	Only upgradeable when RPT is connected to the S3 panel

CAMWorks Compatibility Chart 5

	CAMWorks Compatibility Chart	CAMWorks 1.23.03	7100 StandALone 7.03.02	7100 NetSolo 7.03.02	CAMWorks 2.10.33	CAMWorks 2.11.09	CAMWorks 2.20.25	CAMWorks 2.30.10	CAMWorks 2.40.012	CAMWorks 3.00.016	CAMWorks 3.10.007	CAMWorks 3.20.028	CAMWorks 3.21.002
ILI-MB/S	v 1.04.001	X			X	X	X	X	X	X		X	X
	v1.05.002	X			X	X	X	X	X	X		X	X
	v 1.07.011				X	X	X	X	X	X		X	X
	v2.04.088						X	X	X	X		X	X
	v2.06.003							X	X	X		X	X
	v2.07.061							X	X	X		X	X
	v3.00.116								X	X	X	X	X
	v3.01.051									X	X	X	X
	v3.02.285											X	X
ILDS-MB/S	v1.09.001	X											
	v2.00.002				X	X	X	X	X	X		X	X
	v2.02.011				X	X	X	X	X	X		X	X
	v2.04.086						X	X	X	X		X	X
	v2.06.003							X	X	X		X	X
	v2.07.061							X	X	X		X	X
	v3.00.116								X	X	X	X	X
	v3.01.051									X	X	X	X
	v3.02.285											X	X
NGA	v2.00.691	X		X	X	X	X	X					
	v2.10.014	X		X	X	X	X	X	X	X	X	X	X
	v2.20.024						X	X	X	X	X	X	X
	v2.30.003							X	X	X	X	X	X
	v2.31.001							X	X	X	X	X	X
	v3.00.240								X	X	X	X	X
	v3.10.142											X	X

X*	Supports Stand Alone (SA) or Network with an ILI-MB
X**	Does not support photo CO
X***	Supports Stand Alone (SA) Only
X****	Supports Window 7-64bit Only

CAMWorks Compatibility Chart 6

	CAMWorks Compatibility Chart	CAMWorks 1.23.03	7100 StandALone 7.03.02	7100 NetSolo 7.03.02	CAMWorks 2.10.33	CAMWorks 2.11.09	CAMWorks 2.20.25	CAMWorks 2.30.10	CAMWorks 2.40.012	CAMWorks 3.00.016	CAMWorks 3.10.007	CAMWorks 3.20.022	CAMWorks 3.21.002
ANX	v1.00.049				X	X	X		X	X	X	X	X
	v1.10.005							X	X	X	X	X	X
	v1.20.070								X	X	X	X	X
	v1.30.079											X	X
7100	v6.04.160	X	X	X	X	X	X	X	X	X	X		X
	v7.00.156	X	X	X	X	X	X	X	X	X	X		X
	v7.01.001	X	X	X	X	X	X	X	X	X	X		X
	v7.02.024			X				X	X	X	X	X	X
S3	v1.00.026									X	X		X
	v1.01.019									X	X	X	X
	v1.11.009											X	X
LCD-SLP	v1.00.112									X	X		
	v1.01.123									X	X	X	X
	v1.02.001											X	X
RPT-E3	v1.00.057									X	X	X	X
	v1.01.001									X	X	X	X

X*	Supports Stand Alone (SA) or Network with an ILI-MB
X**	Does not support photo CO
X***	Supports Stand Alone (SA) Only
X****	Supports Window 7-64bit Only

Focal Point Compatibility Chart 7

Focal Point Compatibility Chart		FocalPoint 3.12.125	FocalPoint 3.14.132	FocalPoint 3.16.136	FocalPoint 3.18.176	FocalPoint 3.22.154	FocalPoint 3.24.142
ILI-MB / S	v 1.04.001	X					
	v1.05.002		X	X			
	v 1.07.011		X	X			
	v2.04.088			x			
	v2.06.003			X	X***	X***	X***
	v2.07.061			X	X***	X***	X***
	v3.00.116				X***	X***	X***
	v3.01.051				X***	X***	X***
	v3.02.285						X***
ILI05-MB / S	v1.09.001	X					
	v2.00.002		X	X			
	v2.02.011		X	X			
	v2.04.086			X			
	v2.06.003			X	X***	X***	X***
	v2.07.061			X	X***	X***	X***
	v3.00.116				X***	X***	X***
	v3.01.051				X***	X***	X***
	v3.02.285					X***	X***
NGA	v2.00.691	X	X				
	v2.10.014		X	X			
	v2.20.024			X			
	v2.30.003			X			
	v2.31.001			X	X***	X***	X***
	v3.00.240				X***	X***	X***
	v3.10.125					X***	X***

X*	Supports Stand Alone (SA) or Network with an ILI-MB
X**	Does not support photo CO
X***	Supports Stand Alone (SA) Only
X****	Supports Window 7-64bit Only

Focal Point Compatibility Chart 8

Focal Point Compatibility Chart		FocalPoint 3.12.126	FocalPoint 3.14.132	FocalPoint 3.16.136	FocalPoint 3.18.176	FocalPoint 3.20.108	FocalPoint 3.24.142
ANX	v1.00.049		X	X	X***	X***	X***
	v1.10.005			X	X***	X***	X***
	v1.20.070				X***	X***	X***
	v1.30.079					X***	X***
7100	v6.04.160	X*	X**	X**	X***	X***	X***
	v7.00.156	X*	X **	X**	X***	X***	X***
	v7.01.001	X*	X**	X**	X***	X***	X***
	v7.02.024					X***	X***
S3	v1.00.026					X***	X***
	v1.01.019					X***	X***
	v1.11.009					X***	X***
LCD-SLP	v1.00.112						
	v1.01.123						
	v1.02.001						
RPT-E3	v1.00.057						
	v1.01.001						

X*	Supports Stand Alone (SA) or Network with an ILI-MB
X**	Does not support photo CO
X***	Supports Stand Alone (SA) Only
X****	Supports Window 7-64bit Only

7100 Compatibility Chart 9

7100 Compatibility Document		FCP v2.0	FCP v3.3	FCP v4.0	FCP v5.5	FCP v6.1	FCP v6.5.0	FCP v6.5.2	FCP v7.00.16	FCP v7.01.11	FCP v7.03.02					
7100 Firmware	v2	**X														
	v3		**X													
	v4			**X												
	v5				X											
	v6.1-001					X	X	X	X	X	X					
	v6.2-003					X	X	X	X	X	X					
	v6.3-001					X	X	X	X	X	X					
	v6.3-011					X	X	X	X	X	X					
	v6.4-008					X	X	X	X	X	X					
	v6.4-133					X	X	X	X	X	X					
	v6.4-156					*X	*X	*X	*X	*X	*X					
	V6.4-160					*X	*X	*X	*X	*X	*X					
	v7.0-045					*X	*X	*X	*X	*X	*X					
	v7.0-133					*X	*X	*X	*X	*X	*X					
	V7.0-156					*X	*X	*X	*X	*X	*X					
	v7.0-160					*X	*X	*X	*X	*X	*X					
	v7.1.001								*X	*X	*X					
	v7.1.024										*X					

*X	Use PCB Rev C or Higher UL864
**X	Can be flashed to version 5 along with upgrading FCP
Notes	
1	8th Edition boards support firmware chips v 2.0 through v 6.4-160 but not v7 firmware
2	9th Edition boards support firmware chips v 7 only
3	V2 -V5 flashable up to V5, In order to ugrade to V6 need to replace U3

Gateway & Workstation Compatibility Chart 10

Focal Point Workstation & Gateway Compatibility Chart		WorkStation 3.0.145	WorkStation 3.0.205	WorkStation 3.10.122	WorkStation 3.11.124	WorkStation 3.12.126	WorkStation 3.14.130	WorkStation 3.16.138	WorkStation 3.18.176	WorkStation 3.22.154	WorkStation 3.24.142
BNA	3.10.122			X							
	3.11.124				X						
	3.12.126					X					
	3.14.130						X				
	3.16.132							X			
	3.18.176								X		
	3.20.108								X		
Gate-3	3.11.124				X						
	3.12.126					X					
	3.14.130						X				
	3.16.138							X			
	3.18.176								X		
	3.20.108								X		
	3.22.154									X	X
Gate-3-R	3.12.154					X					
	3.16.228							X			
	3.18.176								X		
	3.20.108								X		
	3.22.154									X	X

NOTE:

1. The BNA gateway is no longer support after V3.20.108
2. V3.22.154 gateway no longer supports Java Script, it uses HTML 5

Focal Point Gateway Compatibility Chart

Focal Point Gateway Compatibility Chart		Windows XP	Windows 7 64 Bit
FPT-Gate	3.2.5	X	
	3.3.2	X	
	3.3.6	X	
	3.10.122	X	
	3.11.124	X	
	3.12.126	X	
	3.14.130	X	
	3.16.132	X	X
	3.18.176		x
	3.20.108		X
FPT-Gate-3	3.11.124	X	
	3.12.126	X	
	3.14.130	X	
	3.16.138	X	X
	3.18.176		X
	3.20.108		X
	2.22.154		X
	3.24.142		X
FPT-Gate-3-R	3.12.154	X	
	3.16.228	X	
	3.18.176		X
	3.20.108		X
	3.22.154		X
	3.24.142		X

Focal Point Workstation Compatibility Chart

Focal Point Workstation Compatibility Chart		Windows XP	Windows 7 64 Bit
WorkStation	3.0.145	X	
	3.0.205	X	
	3.10.122	X	
	3.11.124	X	
	3.12.126	X	
	3.14.130	X	
	3.16.138	X	X
	3.18.176		X
	3.22.154		X
	3.24.142		X

Focal Point Workstation Java/HTML Compatibility Chart

Focal Point Workstation Java/HTML Compatibility Chart		Java V 6	Java V 7	HTML 5
WorkStation	3.0.145			
	3.0.205			
	3.10.122			
	3.11.124			
	3.12.126			
	3.14.130	X		
	3.16.138	X		
	3.18.176		X	
	3.20.108		X	
	3.22.154			X
	3.24.142			X

If you have any questions, please contact Gamewell-FCI Technical Support at 1-800-274-4324.

Sean Murphy
Supervisor
Engineering Technical Support
Gamewell-FCI by Honeywell

Bob Gomersall
Customer Product Manager
Gamewell-FCI by Honeywell