Gamewell FCI FIRE CONTROL INSTRUMENTS by Honeywell

Technical Bulletin

Date: June 09, 2015 No. T15.10

To: All Gamewell-FCI Distributors

Updated Software Compatibility Charts

Making the correct choices concerning E3/S3 firmware, FocalPoint® and CAMWorks!

Our technical department has developed a series of compatibility charts to visually assist in making the correct selection of firmware, as well as the compatible version of CAMWorks required for system upgrades. Please see Compatibility Charts below.

Firmware Compatibility Chart

Chart 1: ILI-MB/S, ILI95-MB/S, ILI-MB/S-PCA and NGA

Firmware Compatibility Document	ILI-MB / S									
	v 1.04.001	v1.05.002	v 1.07.011	v2.04.088	v2.06.003	v2.07.061	v3.00.116	v3.01.051	v3.02.285	v4.00.114
ILI-MB / S										
v 1.04.001										
v1.05.002										
v 1.07.011										
v2.04.088										
v2.06.003										
v2.07.061										
v3.00.116										
v3.01.051										
v3.02.285										
ILI95-MB / S										
v1.09.001	X									
v2.00.002		X								
v2.02.011			X							
v2.04.086				X						
v2.06.003					X					
v2.07.061						X				
v3.00.116							X			
v3.01.051								X		
v3.02.285									X	
ILI-MB/S-PCA										
v4.00.114									X	
NGA										
v2.00.691	X									
v2.10.014		X	X							
v2.20.024				X						
v2.30.003					X					
v2.31.001						X				
v3.00.240							X	X		
v3.10.142									X	X

Firmware Compatibility Document	ILI95-MB / S								
	v1.09.001	v2.00.002	v2.02.011	v2.04.088	v2.06.003	v2.07.061	v3.00.116	v3.01.051	v3.02.285
ILI-MB / S									
v 1.04.001	X								
v1.05.002		X							
v 1.07.011			X						
v2.04.088				X					
v2.06.003					X				
v2.07.061						X			
v3.00.116							X		
v3.01.051								X	
v3.02.285									X
ILI95-MB / S									
v1.09.001	X								
v2.00.002		X							
v2.02.011			X						
v2.04.086				X					
v2.06.003					X				
v2.07.061						X			
v3.00.116							X		
v3.01.051								X	
v3.02.285									X
ILI-MB/S-PCA									
v4.00.114									X***
NGA									
v2.00.691	X								
v2.10.014		X	X						
v2.20.024				X					
v2.30.003					X				
v2.31.001						X			
v3.00.240							X	X	
v3.10.142									X

Firmware Compatibility Document	ILI-MB/S-PCA
	v4.00.114
ILI-MB / S	
v 1.04.001	
v1.05.002	
v 1.07.011	
v2.04.088	
v2.06.003	
v2.07.061	
v3.00.116	
v3.01.051	
v3.02.285	X***
ILI95-MB / S	
v1.09.001	
v2.00.002	
v2.02.011	
v2.04.086	
v2.06.003	
v2.07.061	
v3.00.116	
v3.01.051	
v3.02.285	X***
ILI-MB/S-PCA	
v4.00.114	
NGA	
v2.00.691	
v2.10.014	
v2.20.024	
v2.30.003	
v2.31.001	
v3.00.240	
v3.10.142	X***

Firmware Compatibility Document	NGA						
	v2.00.691	v2.10.014	v2.20.024	v2.30.003	v2.31.001	v3.00.240	v3.10.142
ILI-MB / S							
v 1.04.001	X						
v1.05.002		X					
v 1.07.011		X					
v2.04.088			X				
v2.06.003				X			
v2.07.061					X		
v3.00.116						X	
v3.01.051						X	
v3.02.285							X
ILI95-MB / S							
v1.09.001	X						
v2.00.002		X					
v2.02.011		X					
v2.04.086			X				
v2.06.003				X			
v2.07.061					X		
v3.00.116						X	
v3.01.051						X	
v3.02.285							X
ILI-MB/S-PCA							
v4.00.114							X***
NGA							
v2.00.691	X						
v2.10.014		X					
v2.20.024			X				
v2.30.003				X			
v2.31.001					X		
v3.00.240						X	
v3.10.142							X

X*	Downgrades the ILI to 7100 format
X**	Only upgradeable when RPT is connected to the S3 panel
X***	Only upgradeable when using ILI-MB/S-PCA version of the ILI

Firmware Compatibility Chart (continued)

Chart 2: ANX, 7100, S3, LCD-SLP, and RPT-E3

	Firmware Compatibility Document	ANX					7100					S3					LCD-SLP					RPT-E3		
		v1.00.049	v1.10.005	v1.20.070	v1.30.079		v6.04.160	v7.00.156	v7.01.001	v7.02.024		v1.00.026	v1.01.019	v1.11.009	v1.13.001		v1.00.112	v1.01.123	v1.02.001	v2.00.070		v1.00.057	v1.01.001	
ILI-MB / S	v 1.04.001						X*	X*	X*	X*												X	X**	
	v1.05.002	X					X*	X*	X*	X*												X	X**	
	v 1.07.011	X					X*	X*	X*	X*												X	X**	
	v2.04.088	X					X*	X*	X*	X*												X	X**	
	v2.06.003		X				X*	X*	X*	X*												X	X**	
	v2.07.061		X				X*	X*	X*	X*												X	X**	
	v3.00.116			X			X*	X*	X*	X*												X	X**	
	v3.01.051			X					X*	X*		X	X				X	X				X	X**	
	v3.02.285				X				X*	X*				X	X				X	X		X	X**	
ILI95-MB / S	v1.09.001						N/A	N/A	N/A	N/A												X	X**	
	v2.00.002	X					N/A	N/A	N/A	N/A												X	X**	
	v2.02.011	X					N/A	N/A	N/A	N/A												X	X**	
	v2.04.086	X					N/A	N/A	N/A	N/A												X	X**	
	v2.06.003		X				N/A	N/A	N/A	N/A												X	X**	
	v2.07.061		X				N/A	N/A	N/A	N/A												X	X**	
	v3.00.116			X			N/A	N/A	N/A	N/A												X	X**	
	v3.01.051			X			N/A	N/A	N/A	N/A		X	X				X	X				X	X**	
	v3.02.285				X		N/A	N/A	N/A	N/A				X	X				X	X		X	X**	
ILI-MB/S-PCA	v4.00.114				X***										X***					X***			X**	
NGA	v2.00.691						X	X	X	X												X	X**	
	v2.10.014	X					X	X	X	X												X	X**	
	v2.20.024	X					X	X	X	X												X	X**	
	v2.30.003		X				X	X	X	X												X	X**	
	v2.31.001		X				X	X	X	X												X	X**	
	v3.00.240			X			X	X	X	X		X	X				X	X				X	X**	
	v3.10.142				X				X	X				X	X				x	X		X	X**	

X*	Downgrades the ILI to 7100 format
X**	Only upgradeable when RPT is connected to the S3 panel
X***	Only upgradeable when using ILI-MB/S-PCA version of the ILI

Firmware Compatibility Chart (continued)

Chart 3: ILI-MB/S, ILI95-MB/S, ILI-MB/S-PCA and NGA

	Firmware Compatibility Document	ILI-MB / S									ILI95-MB / S								ILI-MB/S-PCA	NGA						
		v 1.04.001	v1.05.002	v 1.07.011	v2.04.088	v2.06.003	v2.07.061	v3.00.116	v3.01.051	v3.02.285	v4.00.114	v1.09.001	v2.00.002	v2.02.011	v2.04.088	v2.06.003	v2.07.061	v3.00.116	v3.01.051	v3.02.285	v4.00.114	v2.00.691	v2.10.014	v2.20.024	v2.30.003	v2.31.001	v3.00.240	v3.10.142
ANX	v1.00.049		X	X	X								X	X	X								X	X				
	v1.10.005					X	X									X	X								X	X		
	v1.20.070							X	X									X	X								X	
	v1.30.079									X	X									X	X***							X
7100	v6.04.160	X*	X*	X*	X*	X*	X*	X*				N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A		X	X	X	X	X	X	
	v7.00.156	X*	X*	X*	X*	X*	X*	X*				N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A		X	X	X	X	X	X	
	v7.01.001	X*	X*	X*	X*	X*	X*	X*	X*			N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A		X	X	X	X	X	X	
	v7.02.024								X*	X*									N/A	N/A							X	X
S3	v1.00.026								X										X								X	
	v1.01.019								X										X								X	
	v1.11.009									X										X								X
	v1.13.001									X	X									X	X***							X
LCD-SLP	v1.00.112																										X	
	v1.01.123																										X	
	v1.02.001									X	X									X	X***							X
	v2.00.070									X	X									X	X***							X
RPT-E3	v1.00.057									X										X		X	X	X	X	X	X	X
	v1.01.001									X**	X***									X**	X***	X	X	X	X	X	X	X

X*	Downgrades the ILI to 7100 format
X**	Only upgradeable when RPT is connected to the S3 panel
X***	Only upgradeable when using ILI-MB/S-PCA version of the ILI

Firmware Compatibility Chart (continued)

Chart 4: ANX, 7100, S3, LCD-SLP, and RPT-E3

Firmware Compatibility Document		ANX					7100					S3					LCD-SLP					RPT-E3		
		v1.00.049	v1.10.005	v1.20.070	v1.30.079		v6.04.160	v7.00.156	v7.01.001	v7.02.024		v1.00.026	v1.01.019	v1.11.009	v1.13.001		v1.00.112	v1.01.123	v1.02.001	v2.00.070		v1.00.057	v1.01.001	
ANX	v1.00.049						N/A	N/A	N/A	N/A												X	X**	
	v1.10.005						N/A	N/A	N/A	N/A												X	X**	
	v1.20.070						N/A	N/A	N/A	N/A		X	X				X	X				X	X**	
	v1.30.079									N/A				X	X				X	X		X	X**	
7100	v6.04.160	N/A	N/A	N/A																				
	v7.00.156	N/A	N/A	N/A																				
	v7.01.001	N/A	N/A	N/A								X	X	X	X		X	X	X					
	v7.02.024			N/A	N/A							X	X	X	X		X	X	X					
S3	v1.00.026			X					X	X							X	X				X	X**	
	v1.01.019			X					X	X							X	X				X	X**	
	v1.11.009				X					X									X			X	X**	
	v1.13.001				X					X										X			X**	
LCD-SLP	v1.00.112			X					X	X		X	X											
	v1.01.123			X					X	X		X	X											
	v1.02.001				X				X	X				X										
	v2.00.070				X										X									
RPT-E3	v1.00.057	X	X	X	X							X	X	X										
	v1.01.001	X**	X**	X**	X**							X**	X**	X**	X**									

X*	Downgrades the ILI to 7100 format
X**	Only upgradeable when RPT is connected to the S3 panel
X***	Only upgradeable when using ILI-MB/S-PCA version of the ILI

CAMWorks Compatibility Chart

Chart 1: ILI-MB/S, ILI95-MB/S, ILI-MB/S-PCA, NGA

	CAMWorks & Focal Point Compatibility Chart	CAMWorks 1.23.03	7100 StandALone 7.03.02	7100 NetSolo 7.03.02	CAMWorks 2.10.33	CAMWorks 2.11.09	CAMWorks 2.20.25	CAMWorks 2.30.10	CAMWorks 2.40.012	CAMWorks 3.00.016	CAMWorks 3.10.007	CAMWorks 3.20.028	CAMWorks 3.21.002	CAMWorks 3.30.017
ILI-MB/S	v 1.04.001	X			X	X	X	X	X	X		X	X	X
	v1.05.002	X			X	X	X	X	X	X		X	X	X
	v 1.07.011				X	X	X	X	X	X		X	X	X
	v2.04.088						X	X	X	X		X	X	X
	v2.06.003							X	X	X		X	X	X
	v2.07.061							X	X	X		X	X	X
	v3.00.116								X	X	X	X	X	X
	v3.01.051									X	X	X	X	X
	v3.02.285											X	X	X
ILI95-MB/S	v1.09.001	X												
	v2.00.002				X	X	X	X	X	X		X	X	X
	v2.02.011				X	X	X	X	X	X		X	X	X
	v2.04.086						X	X	X	X		X	X	X
	v2.06.003							X	X	X		X	X	X
	v2.07.061							X	X	X		X	X	X
	v3.00.116								X	X	X	X	X	X
	v3.01.051									X	X	X	X	X
	v3.02.285											X	X	X
ILI-MB/S-PCA	v4.00.114													X
NGA	v2.00.691	X		X	X	X	X	X						
	v2.10.014	X		X	X	X	X	X	X	X	X	X	X	X
	v2.20.024						X	X	X	X	X	X	X	X
	v2.30.003							X	X	X	X	X	X	X
	v2.31.001							X	X	X	X	X	X	X
	v3.00.240								X	X	X	X	X	X
	v3.10.142											X	X	X

X*	Supports Stand Alone (SA) or Network with an ILI-MB
X**	Does not support photo CO
X**	Supports Stand Alone (SA) Only
X***	Supports Window 7-64bit Only

CAMWorks Compatibility Chart (continued)

Chart 2: ANX, 7100, S3, LCD-SLP, RPT-E3

	CAMWorks & Focal Point Compatibility Chart	CAMWorks 1.23.03	7100 StandALone 7.03.02	7100 NetSolo 7.03.02	CAMWorks 2.10.33	CAMWorks 2.11.09	CAMWorks 2.20.25	CAMWorks 2.30.10	CAMWorks 2.40.012	CAMWorks 3.00.016	CAMWorks 3.10.007	CAMWorks 3.20.028	CAMWorks 3.21.002	CAMWorks 3.30.017
ANX	v1.00.049				X	X	X		X	X	X	X	X	X
	v1.10.005							X	X	X	X	X	X	X
	v1.20.070								X	X	X	X	X	X
	v1.30.079											X	X	X
7100	v6.04.160	X	X	X	X	X	X	X	X	X	X		X	X
	v7.00.156	X	X	X	X	X	X	X	X	X	X		X	X
	v7.01.001	X	X	X	X	X	X	X	X	X	X		X	X
	v7.02.024			X				X	X	X	X	X	X	X
S3	v1.00.026									X	X		X	X
	v1.01.019									X	X	X	X	X
	v1.11.009												X	X
	v1.13.001													X
LCD-SLP	v1.00.112									X	X			
	v1.01.123									X	X	X	X	
	v1.02.001											X	X	
	v2.00.070													X
RPT-E3	v1.00.057									X	X	X	X	X
	v1.01.001									X	X	X	X	X

X*	Supports Stand Alone (SA) or Network with an ILI-MB
X**	Does not support photo CO
X**	Supports Stand Alone (SA) Only
X***	Supports Window 7-64bit Only

FocalPoint® Compatibility Chart

Chart 1: ILI-MB/S, ILI95-MB/S, ILI-MB/S-PCA, NGA

CAMWorks & Focal Point Compatibility Chart		FocalPoint 3.12.126	FocalPoint 3.14.132	FocalPoint 3.16.136	FocalPoint 3.18.176	FocalPoint 3.22.154	FocalPoint 3.24.142
ILI-MB/S	v 1.04.001	X					
	v1.05.002		X	X			
	v 1.07.011		X	X			
	v2.04.088			x			
	v2.06.003			X	X***	X***	X***
	v2.07.061			X	X***	X***	X***
	v3.00.116				X***	X***	X***
	v3.01.051				X***	X***	X***
	v3.02.285						X***
	v4.00.114						X***
ILI95-MB/S	v1.09.001	X					
	v2.00.002		X	X			
	v2.02.011		X	X			
	v2.04.086			X			
	v2.06.003			X	X***	X***	X***
	v2.07.061			X	X***	X***	X***
	v3.00.116				X***	X***	X***
	v3.01.051				X***	X***	X***
	v3.02.285					X***	X***
ILI-MB/S-PCA	v4.00.114						X***
NGA	v2.00.691	X	X				
	v2.10.014		X	X			
	v2.20.024			X			
	v2.30.003			X			
	v2.31.001			X	X***	X***	X***
	v3.00.240				X***	X***	X***
	v3.10.142					X***	X***

X*	Supports Stand Alone (SA) or Network with an ILI-MB
X**	Does not support photo CO
X**	Supports Stand Alone (SA) Only
X***	Supports Window 7-64bit Only

FocalPoint® Compatibility Chart (continued)

Chart 2: ANX, 7100, S3, LCD-SLP, RPT-E3

CAMWorks & Focal Point Compatibility Chart		FocalPoint 3.12.126	FocalPoint 3.14.132	FocalPoint 3.16.136	FocalPoint 3.18.176	FocalPoint 3.22.154	FocalPoint 3.24.142
ANX	v1.00.049		X	X	X***	X***	X***
	v1.10.005			X	X***	X***	X***
	v1.20.070				X***	X***	X***
	v1.30.079					X***	X***
7100	v6.04.160	X*	X**	X**	X***	X***	X***
	v7.00.156	X*	X**	X**	X***	X***	X***
	v7.01.001	X*	X**	X**	X***	X***	X***
	v7.02.024					X***	X***
S3	v1.00.026					X***	X***
	v1.01.019					X***	X***
	v1.11.009					X***	X***
	v1.13.001						
LCD-SLP	v1.00.112						
	v1.01.123						
	v1.02.001						
	v2.00.070						
RPT-E3	v1.00.057						
	v1.01.001						

X*	Supports Stand Alone (SA) or Network with an ILI-MB
X**	Does not support photo CO
X**	Supports Stand Alone (SA) Only
X***	Supports Window 7-64bit Only

7100 Compatibility Chart

7100 Compatibility		FCP v2.0	FCP v3.3	FCP v4.0	FCP v5.5	FCP v6.1	FCP v6.5.0	FCP v6.5.2	FCP v7.00.16	FCP v7.01.11	FCP v7.03.02
7100 Firmware	v2	**X									
	v3		**X								
	v4			**X							
	v5				X						
	v6.1-001					X	X	X	X	X	X
	v6.2-003					X	X	X	X	X	X
	v6.3-001					X	X	X	X	X	X
	v6.3-011					X	X	X	X	X	X
	v6.4-008					X	X	X	X	X	X
	v6.4-133					X	X	X	X	X	X
	v6.4-156					*X	*X	*X	*X	*X	*X
	V6.4-160					*X	*X	*X	*X	*X	*X
	v7.0-045					*X	*X	*X	*X	*X	*X
	v7.0-133					*X	*X	*X	*X	*X	*X
	V7.0-156					*X	*X	*X	*X	*X	*X
	v7.0-160					*X	*X	*X	*X	*X	*X
	v7.1.001								*X	*X	*X
	v7.2.024										*X

*X	Use PCB Rev C or Higher UL864
**X	Can be flashed to version 5 along with upgrading FCP
	Notes
1	8th Edition boards support firmware chips v 2.0 through v 6.4-160 but not v7 firmware
2	9th Edition boards support firmware chips v 7 only
3	V2 -V5 flashable up to V5, In order to ugrade to V6 need to replace U3

Gateway & Workstation Compatibility Chart

Focal Point Workstation & Gateway Compatibility Chart		WorkStation 3.0.145	WorkStation 3.0.205	WorkStation 3.10.122	WorkStation 3.11.124	WorkStation 3.12.126	WorkStation 3.14.130	WorkStation 3.16.138	WorkStation 3.18.176	WorkStation 3.22.154	WorkStation 3.24.142
BNA	v3.2.5	X	X								
	v3.3.2	X	X								
	v3.3.6	X	X								
	v3.10.122			X							
	v3.11.124				X						
	v3.12.126					X					
	v3.14.130						X				
	v3.16.132							X			
	v3.18.176								X		
	v3.20.108								X		
Gate-3	v3.11.124				X						
	v3.12.126					X					
	v3.14.130						X				
	v3.16.138							X			
	v3.18.176								X		
	v3.20.108								X		
	v3.22.154									X	
	v3.24.142										X
Gate-3-R	v3.12.154					X					
	v3.16.228							X			
	v3.18.176								X		
	v3.20.108								X		
	v3.22.154									X	
	v3.24.142										X

Note:
1. The BNA gateway is no longer support after v3.20.108
2. V3.22.154 gateway no longer supports Java Script, it uses HTML 5

FocalPoint® Gateway & Workstation Compatibility Chart

Chart 1: FocalPoint® Gateway Compatibility

Focal Point Gateway Compatibility Chart		Windows XP	Windows 7 64 Bit
FPT-Gate	v3.2.5	X	
	v3.3.2	X	
	v3.3.6	X	
	v3.10.122	X	
	v3.11.124	X	
	v3.12.126	X	
	v3.14.130	X	
	v3.16.132	X	X
	v3.18.176		x
	v3.20.108		X
FPT-Gate-3	v3.11.124	X	
	v3.12.126	X	
	v3.14.130	X	
	v3.16.138	X	X
	v3.18.176		X
	v3.20.108		X
	v2.22.154		X
	v3.24.142		X
FPT-Gate-3-R	v3.12.154	X	
	v3.16.228	X	X
	v3.18.176		X
	v3.20.108		X
	v3.22.154		X
	v3.24.142		X

Chart 2: FocalPoint® Workstation Compatibility

Focal Point Workstation Compatibility Chart		Windows XP	Windows 7 64 Bit
WorkStation	v3.0.145	X	
	v3.0.205	X	
	v3.10.122	X	
	v3.11.124	X	
	v3.12.126	X	
	v3.14.130	X	
	v3.16.138	X	X
	v3.18.176		X
	v3.22.154		X
	v3.24.142		X

Chart 3: FocalPoint® Workstation Java/HTML Compatibility

Focal Point Workstation Java/HTML Compatibility Chart		Java V 6	Java V 7	HTML 5
WorkStation	v3.0.145			
	v3.0.205			
	v3.10.122			
	v3.11.124			
	v3.12.126			
	v3.14.130	X		
	v3.16.138	X		
	v3.18.176		X	
	v3.20.108		X	
	v3.22.154			X
	v3.24.142			X

For additional questions or support on system compatibility, please contact Gamewell-FCI Technical Support at 1-800-274-4324

Sean Murphy
Supervisor,
Engineering Technical Support
Gamewell-FCI by Honeywell

Chuck Han
Product Marketing
Gamewell-FCI by Honeywell