

AMM-4



ADDRESSABLE MONITOR MODULE



DESCRIPTION

The Addressable Monitor Module AMM-4 features a single Style D, Class A circuit. It may also be configured as a Style B, Class B initiating circuit with end of line resistor. This module provides an address for any device or group of devices connected to this circuit. Any alarm initiating devices with normally open (N.O.) dry contacts, such as heat detectors, linear heat detection devices, projected beam smoke detectors, 4-wire smoke detectors, water flow switches, tamper switches, manual stations, etc. may be installed in this circuit.

The AMM-4 module is designed for installation in the signaling line circuit of any FCI analog addressable control panel. The signaling line circuits of FCI analog addressable panels are designed to accommodate up to 99 monitor modules per circuit.

The initiating circuit of the AMM-4 has a maximum line resistance of 40 ohms, allowing the module to accommodate a number of initiating devices at a distance from the module.

The AMM-4 is designed to mount in a 4" square junction box 2 1/8" deep.



FEATURES

- Compact Size Allows Easy Installation
- Class A, Style D, or Class B, Style B Initiating Circuit
- 40 Ohm Line Resistance for Initiating Circuit
- Accommodates any N/O Dry Contact Device

AGENCY APPROVALS

UL S1949 **EM** 3006398

NYC MEA 427-91-E Vol. III

CSFM Approved

TECHNICAL INFORMATION

Supervisory current .0004 amp. Alarm current .00575 amp.

Operating temperature 32 to 120°F (0 to 49° C) Relative humidity 10 to 93% (non-condensing)

Dimensions 4 1/2" H x 4" W x 1 1/4" D (3.3 x 5.5 x 1.25 cm)

ORDERING INFORMATION

Part Number Model Description

190-00003 AMM-4 Addressable Monitor Module, Single circuit, Style D, Class A

Specifications are provided for information only, are not intended to be used for installation purposes, and are believed to be accurate. However, no responsibility is assumed by Fire Control Instruments, Inc. for their use. Specifications subject to change without notice.