



by Honeywell

600 Series Remote Annunciators

Description

The 600 Series, Remote Annunciators (RAN2 and RAN2-RC) provide remote display and control capabilities. Each RAN device is connected to the main 600 Series Fire Alarm Control Panel (FACP) via a serial communications port. The RAN interprets the instructions from the main FACP, initiating a programmed response, and retransmitting the instructions to the next device.

Gamewell-FCI 600 Series Systems can accommodate up to 64 devices connected to the serial communications port. In addition to the Remote Annunciator (RAN2), these devices include Serial Annunciator drives (SAN) and Remote Printer Interfaces (RPI). These devices comprise the Gamewell-FCI Status Control Network. Each device contains its own microprocessor and can be programmed independently. A network of devices can be programmed directly from a single device, saving valuable installation time.

The Remote Alphanumeric Display (RAN2) is fully supervised and includes dual serial ports for network connection. The RAN2 model displays the user text from the main system. The remote control version (RAN2-RC) includes the following seven switches:

- | | |
|----------------------|--------------------------|
| • Remote Acknowledge | • Display 1st Event |
| • Reset | • Display Next Event |
| • Signal Silence | • Display Previous Event |
| • Lamp Test | |

The basic RAN2 model includes a scroll switch only. The scroll switch is used to review multiple events on the system. The remote control versions are provided with a seven-position switch bank and eight LEDs for system annunciation. The switches provide remote control of the connected system. A key switch enables and disables the switches to prevent unauthorized operation.

The Status Control Network is connected to the main 600 Series control panel via an RS-232 data communications line. The SIM-232 module is used to provide an isolated RS-232 output from the main CPU of the IF632, IF654, and IF658 FACPs. The IF602 and IF610 have a built-in RS-232 port.

UL® is a registered trademark of Underwriters Laboratories, Inc.

600 Series RAN2, RAN2-RC Models



RAN2, RAN2-RC

Features

- Listed per ANSI/UL® Standard 864, 9th Edition
- Backlit LCD alphanumeric display, 4-lines by 40-characters
- Up to 64 devices supported on a single 600 Series control panel
- Field-programming via PC
- Dual optically-isolated serial ports
- Microprocessor controlled
- Supervised
- Allows remote system control
- Surface-mount and flush-mount models available
- Adjustable viewing angle
- Network monitoring capabilities

An ISO 9000-2000 Company



7120-1703:137

GAMEWELL-FCI

12 Clintonville Road, Northford, CT 06472-1610 USA • Tel: (203) 484-7161 • Fax: (203) 484-7118

Specifications are for information only, are not intended for installation purposes, and are subject to change without notice. No responsibility is assumed by Gamewell-FCI for their use.

©2009 Honeywell International Inc. All rights reserved.

www.gamewell-fci.com

CS-2025 Rev. B page 1 of 2

Applications

Remote alphanumerics are ideal wherever text-based annunciation of system activity is required. Since the RAN can also control system activity, there is no additional hardware required to complete a status and command center for a system of any size.

Engineer’s Specifications

Remote annunciation and control for the main control panel shall be supplied where indicated. Remote annunciation and control shall be accomplished via the RS-232 data communications line. It shall be possible to add up to 64 devices to the communication line. It shall be possible to mix serial annunciators, printers and LCD alphanumeric displays on a single line without the need for special software. Devices shall not be placement-sensitive. All devices shall be individually field programmable and independent from each other. The device shall be identified with Gamewell-FCI part numbers.

Specifications

Input Power:	24 VDC
Standby Current:	0.04A normal (backlight off)
Alarm Current:	0.04A plus external load
Operating Temperature:	+34° F to +120° F (0° C to +49° C)
Relative Humidity:	93% non-condensing
Protocol (Xon/Xoff)	2400 baud, non parity, 8 data bits, 1 stop bit
Dimensions:	
Surface Mount (-S):	5.125" H x 9.875" W (13.018 H x 25.083 W cm)
Flush mount (-F):	6.125" H x 10.875" W (15.558 H x 27.623 W cm)
Backbox (RAN2-BB):	5.25" H x 10.10" W x 2.44" D (13.335 H x 25.654 W x 6.198 D cm)

Ordering Information

Part Number	Description
GWRAN2-S	Remote annunciator, surface mount, 4-line x 40-character alphanumeric display.
GWRAN2-F	Remote annunciator, flush mount, 4-line x 40-character alphanumeric display.
GWRAN2-RCS	Remote annunciator, surface mount, 4-line x 40-character alphanumeric display with remote control.
GWRAN2-RCF	Remote annunciator, flush mount, 4-line x 40-character alphanumeric display with remote control.
GWSIM-232	Serial interface module, mounts in 600 Series control (IF632, IF654, IF658) to supply RS-232 outputs. Not required for IF602 and IF610 systems.
GW70703	Programming cable Programmed via PC-based "SAN/RAN Program"). Note: This program is only available to Gamewell-FCI Authorized Distributors.