

SpectrAlert® Advance™

Selectable-Output Low Frequency Sounders & Sounder Strobes



Audio Visual Equipment

General

The SpectrAlert® Advance™ series offers the most versatile and easy-to-use line of low frequency sounder and low frequency sounder strobes in the industry. With white and red plastic housings, dual listed for wall and ceiling mounting, SpectrAlert Advance can meet virtually any application requirement.

Like the entire SpectrAlert Advance product line, all-mount low frequency sounder, and low frequency sounder strobes include a variety of features that increase their application versatility while simplifying installation. All devices feature plug-in designs with minimal intrusion into the black box, making installations fast and foolproof while virtually eliminating costly and time-consuming ground faults.

To further simplify installation and protect devices from construction damage, SpectrAlert Advance use a universal mounting plate with an onboard shorting spring, so installers can test wiring continuity before the device is installed.

Installers can also easily adapt devices to suit a wide range of application requirements using field-selectable candela settings, automatic selection of 12 or 24-volt operation, and a rotary switch for low frequency sounder tones.

Features

- Plug-in design with minimal intrusion into the back box.
- Tamper-resistant construction.
- Field-selectable candela settings on wall units: 135, 150, 177, and 185.
- Rotary switch for low frequency sounder tone.
- Universal mounting plate for wall units.
- Mounting plate shorting spring checks wiring continuity before device installation.
- Electrically compatible with legacy SpectrAlert Advance devices.
- Compatible with MDL3 sync module.
- Listed for ceiling or wall mounting.

Architect/Engineer Specifications

GENERAL

SpectrAlert Advance low frequency sounder and low frequency sounder strobes shall mount to a standard 4x4x1-1/2" back box, 4-inch octagon back box, or double-gang box. Two-wire products shall also mount to a single-gang 2x4x1-7/8" back box. A universal mounting plate shall be used for mounting products. The notification appliance circuit wiring shall terminate at the universal mounting plate. Also, SpectrAlert Advance products, when used with the Sync-Circuit™ Module accessory, shall be powered from a non-coded notification appliance circuit output and shall operate on a nominal 12 or 24 volts. When used with the Sync-Circuit Module, 12-volt-rated notification appliance circuit outputs shall operate between 8.5 and 17.5 volts; 24-volt-rated notification appliance circuit outputs shall operate between 16.5 and 33 volts. Indoor SpectrAlert Advance products shall operate between 32 and 120 degrees Fahrenheit from a regulated DC or full wave rectified unfiltered power supply. Low Frequency Sounder strobes



shall have field-selectable candela settings including 135, 150, 177, and 185.

LOW FREQUENCY SOUNDER

The low frequency sounder and the Sync-Circuit™ MDL3 Module accessory, if used, shall be powered from a notification appliance circuit output and shall operate on a nominal 12 or 24 volts (includes fire alarm panels with built in sync). When used with the Sync-Circuit™ MDL3, 12-volt rated notification appliance circuit outputs shall operate between 8.5 and 17.5 volts; 24-volt rated notification appliance circuit outputs shall operate between 16.5 to 33 volts. If the notification appliances are not UL 9th edition listed with the corresponding panel or power supply being used, then refer to the compatibility listing of the panel to determine maximum devices on a circuit. The low frequency sounder has an option to switch between temporal three pattern, non-temporal (continuous) pattern and coded supply. The low frequency sounder shall operate on a coded or non-coded power supply.

LOW FREQUENCY SOUNDER STROBE COMBINATION

The low frequency sounder strobe shall be approved for fire protective service. The low frequency sounder strobe shall be wired as a primary-signaling notification appliance and comply with the Americans with Disabilities Act requirements for visible signaling appliances, flashing at 1 Hz over the strobe's entire operating voltage range. The strobe light shall consist of a xenon flash tube and associated lens/reflector system. The sounder shall have an option to switch between a temporal three pattern and a non-temporal (continuous) pattern. These options are set by a multiple position switch. The low frequency sounder on low frequency sounder strobe models shall operate on a non-coded power supply.

SYNCHRONIZATION MODULE

The module shall synchronize SpectrAlert strobes at 1 Hz and low frequency sounder at temporal three. Also, while operating the strobes, the module shall silence the low frequency sounder on low frequency sounder strobe models over a single pair of wires. The module shall mount to a 1-11/16x4-11/16x2-1/8-inch back box. The module shall also control two Style Y (Class B) circuits or one Style Z (Class A) circuit. The module shall synchronize multiple zones. Daisy chaining two or more synchronization modules together will synchronize all the zones they control. The module shall not operate on a coded power supply.

Physical/Electrical Specifications

Standard Operating Temperature: 32°F to 120°F (0°C to 49°C).

Humidity Range: 10 - 93% non-condensing.

Strobe Flash Rate: 1 flash per second.

Nominal Voltage Low Frequency Sounder: Regulated 12 DC/FWR or regulated 24 DC/FWR.

Nominal Voltage Range Low Frequency Sounder Strobe: Regulated 24 VDC/FWR

Operating Voltage Range: 8 to 17.5V (12V nominal) or 16 to 33 V (24 V nominal).

Operating Voltage Range MDL3 Sync Module: 8.5 to 17.5V (12V nominal) or 16.5 to 33 V (24 V nominal).

Input Terminal Wire Gauge: 12 to 18 AWG.

Wall-Mount Dimensions (including lens): 6.4 inches L x 4.7 inches W x 2.5 inches D (162mm L x 119mm W x 64mm D).

Sounder Dimensions: 5.6 inches L x 4.7 inches W x 1.3 inches D (142mm L x 119mm W x 33mm D).

Low Frequency Sounder/Strobe with Surface Mount Back Box Dimensions (SBBR, SBBW): 6.4 inches L x 4.7 inches W x 4.3 inches D (162mm L x 120mm X x 108mm D).

Low Frequency Sounder with Surface Mount Back Box Dimensions (SBBR, SBBW): 5.7 inches L x 4.8 inches W x 3 inches D (145mm L x 120mm X x 76mm D).

UL Current Draw

UL MAXIMUM STROBE CURRENT DRAW (MA RMS)

		8-17.5 Volts		16-33 Volts	
	Candela	DC	FWR	DC	FWR
High Candela Range	135	N/A	N/A	228	207
	150	N/A	N/A	246	220
	175	N/A	N/A	281	251
	185	N/A	N/A	286	258

UL MAXIMUM LOW FREQUENCY CURRENT DRA (MA RMS)

		8-17.5 Volts		16-33 Volts	
Sound Pattern	dB	DC	FWR	DC	FWR
Temporal	High	191	262	138	166
Continuous	High	292	384	138	208
Coded	High	292	388	153	205

UL MAXIMUM CURRENT DRAW (MA RMS), 2-WIRE LOW FREQUENCY SOUNDER STROBE, HIGH CANDELA RANGE (135 - 185 CD)

		16-33 Volts				16-33 Volts				
DC Input	135	150	177	185	FWR Input	135	150	177	185	
Temporal	277	292	325	344	Temporal	296	309	343	351	
Continuous	337	362	387	417	Continuous	393	395	432	433	

Low Frequency Sounder Tones and Sound Output Data

LOW FREQUENCY SOUNDER AND LOW FREQUENCY SOUNDER STROBE OUTPUT (DBA)

		24-Volt Nominal							
		8-17.5 Volts		16-33 Volts		Reverberant		Anechoic	
Switch Position	Sound Pattern	DC	FWR	DC	FWR	DC	FWR	DC	FWR
1	Temporal	76	76	76	76	76	76	86	86
2	Continuous	80	80	80	80	80	80	90	90
3*	Coded	80	80	80	80	80	80	90	90

* Sounder ratings provided are for continuous voltage as provided by the NAC,

Agency Listings and Approvals

These listings and approvals below apply to the SpectrAlert Advance series. In some cases, certain modules or applications may not be listed by certain approval agencies, or listing may be process. Consult factory for latest listing status.

- **UL Listed:** S4011, S5512
- **CSFM:** 7135-1653:0223 (HR-LF, HW-LF), 7125-1653:0224 (P2HR-LF, P2WH-LF)
- **FM:** 3047563

Ordering Information

P2RH-LF: 2-wire wall low frequency sounder strobe, High cd, red.

P2WH-LF: 2-wire wall low frequency sounder strobe, High cd, white.

HR-LF: low frequency sounder, red.

HW-LF: low frequency sounder, white.

BBS-2: back box skirt, wall red.

BBSW-2: back box skirt, wall, white.

SBBR: surface mount back box, wall, red.

SBBW: surface mount back box, wall, white.

TR-HS: trim ring, wall, red.

TRW-HS: trim ring, wall white.

NOTE: "High cd" refers to strobes that include 135, 150, 177 and 185 candela settings.

FireLite® Alarms and SpectrAlert® are registered trademarks of and SpectrAlert® Advance™ is a trademark of Honeywell International, Inc. ©2014 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.



This document is not intended to be used for installation purposes.
We try to keep our product information up-to-date and accurate.
We cannot cover all specific applications or anticipate all requirements.
All specifications are subject to change without notice.

For more information, contact Fire•Lite Alarms. Phone: (800) 627-3473, FAX: (877) 699-4105.
www.firelite.com