VHF & UHF Digital Signal Boosters
136 - 174 MHz & 450 - 512 MHz

HONBDA Series

Product Features

- Fully digital signal boosters, FPGA-based on Standards and Codes
- Uplink and Downlink Squelch, per channel and per time slot on channel selective mode
- User adjustable gain control, UL and DL Independent, per band, per channel and per time slot on channel selective mode
- Automatic gain control per band, per channel, and per time slot on channel selective mode
- Weatherproof enclosure, NEMA4
- NFPA compliant with dry contact alarms
- Channel Selective, software programmable, 32 channels per band and BW adjustable filters per band
- Auto diagnostic
- Built-in spectrum analyzer
- Single VHF or UHF and dual band options
- Simultaneous dual band 136 - 174 MHz & 450 - 512 MHz with multiple sub band options in UHF
- Preserves far-end communications
- Preserves BTS UL sensitivity
- 3 Year Warranty
- Buy American Compliant: Meets the definition of Domestic Construction Material under the Buy American Act
- FCC (Federal Communications Commission-US)
- Industrial Canada (IC) Compliant
- IFC 2015, 2018, 2021 Edition Standards
- ISO 9001 Compliant
- NFPA 72 2013 Edition, NFPA 1221 2016 2019 Edition and NFPA 1225 2022 Edition
- RoHS Compliant
- UL2524 3rd Edition Listing with SGS, Nationally Recognized Testing Laboratory (NRTL) approved by OSHA for UL2524



Remote



Master

Applications

- For P25 Phase 1 and 2, TETRA, TETRAPOL, NXDN, DMR, Conventional, MPT1327, among others
- Indoor Coverage: Tunnels and Mobile Fast-Deploy Communication Units
- Outdoor Coverage: Oil rigs, stadiums, dense urban areas, rural areas, cliffs

Specification	Value
Type	Digital Signal Boosters
Internal Duplexer	Multiple bandwidth options available
Simplex Option	Configurable per channel
Power Supply	110 VAC 60 Hz & +24 VDC
Power Consumption	Single Band 60 W; Dual Band 70 W
Frequency Range	VHF: 136-174 MHz/UHF: 450 - 512 MHz
Passband Bandwidth (Minimum)	100 KHz to full band or Channel Selective (After Upgrade to Class A)
BWA Filters	Adjustable from 100kHz to full band in step in steps of 50kHz
Number of BWA Filters	2 per band
Number of Channels	32 per band
Number of Passband	2 BWA per band or 32 channel filters + 2 BWA per band
Channel Filter Options	100 KHz, 75 KHz, 62.5 KHz, 50 KHz, 37.5 KHz, 25 KHz & 12.5 KHz (Depends of Configuration)
Gain (Maximum)	85 +/- 2.0 dB
Passband Ripple	+/-3 dB
Gain (Manual Control)	28 dB range, digitally controlled in 1 dB steps, per link, per band

fiplex by Honeywell

Specification	Value
Antenna Isolation	Max Gain +20 dB
Composite Output Power (DL)	VHF: +24 dBm, UHF: +30 dBm
Composite Output Power (UL)	VHF & UHF: +24 dBm per band
IM and Spurious Generation	< -13 dBm
Noise Figure	9.0 dB at Maximum Gain
Group Delay	• Channel Selective 100 KHz, 12.6 µS • Channel Selective 75 KHz, 14.9 µS • Channel Selective 62.5 KHz, 16.8 µS • Channel Selective 50 KHz, 19.6 µS • Channel Selective 37.5 KHz, 24.1 µS • Channel Selective 25 KHz, 33.4 µS • Channel Selective 12.5 KHz, 62.1 µS • Or Band Selective: 3.5 to 6.5 µS depending on BWA after Class A upgrade
Maximum Input Power (No Damage)	+5 dBm (UL), +5 dBm (DL)
Maximum Input Power (Normal Operation)	0 dBm (UL), -35 dBm (DL)
RF Connectors	N (f) as standard
RF Input/Output Impedance	50 Ohms (Ω)
Uplink Squelch Function	Yes, user selectable, to avoid UL noise when no carriers present, per band, per time slot and per channel (on the channel selective mode)
Self Diagnostic Platform	Microprocessor Based
Alarms	• Amplifiers Status • Power Amplifiers Status • Power Supply Failure • Battery Backup Failure • Temperature • AGC • RF Overload • Poor Antenna Isolation.
Housing/Enclosure Rating	NEMA4
Operating Temperature Range	-13º to 131º F (-25º to +55º C)
Cooling	Natural Convection
Weight	52.9 lbs (24 kg)
Dimension	Cabinet Type C: 27.2 x 20.0 x 9.0 in (690.88 x 508 x 228.6mm) Cabinet Type E: 30 x 24 x 14 in (762 x 609.6 x 345 mm)
Mounting	Wall Mounting (Rack Mounting Option Available)
MTBF	50,000 hours
Local Management and Supervising	Local access via USB Connection
Remote Management and Supervising	Remote access via Ethernet Connection

* Value valid for non duplexed units. This value can change depending on the filtering insertion loss of the duplexer.

Normative/License/Certification	Value
FCC ID	P3TDH14-1A
UL ID	SGSNA/20/SUW/00131X

WARNING: This is NOT a CONSUMER device. It is designed for installation by the FCC LICENSEES and QUALIFIED INSTALLERS. You MUST have an FCC LICENSE or express consent of an FCC Licensee to operate this device. Unauthorized use may result in significant forfeiture penalties, including penalties in excess of $100,000 for each continuing violation.

Ordering Information

HONBDA-A-VNL: DIGITAL SIGNAL BOOSTER.VHF 136-174MHz, +24dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, No Internal Duplexer,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-V2L: VHF BDA,0.25W,2MHz,ACDC

HONBDA-A-V3L: DIGITAL SIGNAL BOOSTER.VHF 136-174MHz, +24dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 3.5MHz BW internal Duplexer,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VUN2L: VHF&UHF U BDA, 0.25W & 1W, ND&2MHz, ACDC

HONBDA-A-VUN4L: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: Band#1 Broadband Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VUN5L: VHF&UHF U BDA, 0.25W&1W, ND&5MHz, ACDC

HONBDA-A-VUN04L: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: Band#1 Narrow Filter Band#2: Broadband Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VUN22L: VHF&UHF U BDA, 0.25W&1W, ND&2-2MHz, ACDC

HONBDA-A-VUNMDAL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 453-454/458-459 & 460-462/465-467MHz internal Duplexer,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VUT2L: VHF&UHF BDA, 0.25W&1W, 2&NDMHz, ACDC

HONBDA-A-VU22L: VHF&UHF U BDA, 0.25W&1W, 2&2MHz, ACDC

HONBDA-A-VU24L: VHF&UHF U BDA, 0.25W&1W, 2&4MHz, ACDC

HONBDA-A-VU25L: VHF&UHF U BDA, 0.25W&1W, 2&5MHz, ACDC

HONBDA-A-VU204L: VHF&UHFU BDA, 0.25W&1W, 2&0.7-4MHz, ACDC

HONBDA-A-VU222L: VHF&UHF U BDA, 0.25W&1W, 2&2-2MHz, ACDC

HONBDA-A-VU2MDAL: VHF&UHF U BDA,0.25W&1W, 2&MDAMHz, ACDC

HONBDA-A-VUT3NL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: No Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VU32L: VHF&UHF U BDA, 0.25W&1W, 3&2MHz, ACDC

HONBDA-A-VU34L: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: Band#1 Broadband Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VU35L: VHF&UHF U BDA, 0.25W&1W, 3&5MHz, ACDC

HONBDA-A-VU304L: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: Band#1 Narrow Filter Band#2: Broadband Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VU322L: VHF&UHF U BDA, 0.25W&1W, 3&2-2MHz, ACDC

HONBDA-A-VU3MDAL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 453-454/458-459 & 460-462/465-467MHz internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VUTNNL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: No internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VTN0L: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: Band#1 Narrow Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VTN1L: VHF&UHF T BDA, 0.25W&1W, ND&1.5MHZ, ACDC

HONBDA-A-VTN2L: VHF&UHF T BDA, 0.25W&1W, ND&2MHZ, ACDC

HONBDA-A-VTN00L: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: Band#1 Narrow Filter Band#2: Narrow Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VTN11L: VHF&UHF T BDA,0.25W&1W,ND&15-15MHZ, ACDC

HONBDA-A-VTN02L: VHF&UHF T BDA,0.25W&1W,ND&07-15MHZ, ACDC

HONBDA-A-VTNRWCL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 483.4-484.5/486.4-487.5 & 488.5-489/491.5-492MHz internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VT20L: VHF&UHF T BDA, 0.25W&1W, 2&0.7MHZ, ACDC

HONBDA-A-VT21L: VHF&UHF T BDA, 0.25W&1W, 2&1.5MHZ, ACDC

HONBDA-A-VT22L: VHF&UHF T BDA, 0.25W&1W, 2&2MHZ, ACDC

HONBDA-A-VT200L: VHF&UHF T BDA, 0.25W&1W, 2&07-07MHZ, ACDC

HONBDA-A-VT211L: VHF&UHF T BDA, 0.25W&1W,2&15-15MHZ, ACDC

HONBDA-A-VT2RWCL: VHF&UHF T BDA,0. 25W&1W, 2&RWC, ACDC

HONBDA-A-VT30L: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: Band#1 Narrow Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VT31L: VHF&UHF T BDA, 0.25W&1W, 3&0.7MHZ, ACDC

HONBDA-A-VT32L: VHF&UHF T BDA, 0.25W&1W, 3&2MHZ, ACDC

HONBDA-A-VT300L: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: Band#1 Narrow Filter Band#2: Narrow Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VT311L: VHF&UHF T BDA, 0.25W&1W, 3&15-15MHZ, ACDC

HONBDA-A-VT3RWCL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 483.4-484.5/486.4-487.5 & 488.5-489/491.5-492MHz internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-U2L: UHF U BDA, 1W, 2MHz, ACDC

HONBDA-A-U4L: DIGITAL SIGNAL BOOSTER.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: Broadband Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-U24L: UHF U BDA, 1W, 2-4MHz, ACDC

HONBDA-A-UMDA: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 453-454/458-459 & 460-462/465-467 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-U22L: UHF U BDA, 1W, 2-2MHz, ACDC

HONBDA-A-U04L: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: Narrow Filter - Band #2: Broadband Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-UNL: UHF BDA, 1W, ND, ACDC

HONBDA-A-UTNL: DIGITAL SIGNAL BOOSTER.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, No internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-UT02L: UHF BDA, 1W, 0.7-2MHz, ACDC

HONBDA-A-UT12L: UHF BDA, 1W, 1.5-2MHz, ACDC

HONBDA-A-UT22L: UHF BDA, 1W, 2-2MHz, ACDC

HONBDA-A-UT002L: UHF BDA, 1W, 0.7-2-2MHz, ACDC

HONBDA-A-UTMDA0L: DIGITAL SIGNAL BOOSTER TRIPLE SUB BAND.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 453-454/458-459MHz - Band #2: 460-462/465-467MHz - Band #3: Narrow Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-T0L: DIGITAL SIGNAL BOOSTER.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: Narrow Filter, Internal Duplexer,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-T1L: UHF T BDA, 1W, 1.5MHz, ACDC

HONBDA-A-T2L: UHF T BDA, 1W, 2MHz, ACDC

HONBDA-A-T00L: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: Narrow Filter - Band #2: Narrow Filter, internal Duplexer ,UL2524 2nd Edition Listed

FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-T01L: UHF T BDA, 1W, 0.7-1.5MHz, ACDC

HONBDA-A-T11L: UHF T BDA, 1W, 1.5-1.5MHz, ACDC

HONBDA-A-T12L: UHF T BDA, 1W, 1.5-2MHz, ACDC

HONBDA-A-TRWCL: DIGITAL SIGNAL BOOSTER.UHF 483.4-484.5/486.4-487.5 & 488.5-489/491.5-492 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-TWMOL: DIGITAL SIGNAL BOOSTER.UHF 489.5-491/492.5-494 & 496.3-497/499.3-500 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Internal Duplexer,UL2524 2nd Edition Listed HONEYWELL Digital BDA

HONBDA-A-V1A-1:DIGITAL SIGNAL BOOSTER.VHF 136-150MHz, +13dBm, NFPA, class A, AC & DC, ACF 1 channel internal Duplexer, UL2524 2nd Edition Listed HONEYWELL Digital BDA

HONBDA-A-V2A-1: DIGITAL SIGNAL BOOSTER.VHF 136-150MHz, +13dBm, NFPA, class A, AC & DC, ACF 2 channel internal Duplexer, UL2524 2nd Edition Listed HONEYWELL Digital BDA

HONBDA-A-V1A-2: DIGITAL SIGNAL BOOSTER.VHF 150-174MHz, +13dBm, NFPA, class A, AC & DC, ACF 1 channel internal Duplexer ,UL2524 2nd Edition Listed HONEYWELL Digital BDA

HONBDA-A-V2A-2:DIGITAL SIGNAL BOOSTER.VHF 150-174MHz, +10dBm, NFPA, class A, AC & DC, ACF 2 channel internal Duplexer ,UL2524 2nd Edition Listed HONEYWELL Digital BDA

HONBDA-A-V2DL: DIGITAL SIGNAL BOOSTER.VHF 136-174MHz, +24dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 2MHz BW internal Duplexer Donor side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-V3DL: DIGITAL SIGNAL BOOSTER.VHF 136-174MHz, +24dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 3.5MHz BW internal Duplexer Donor side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-V2SL: DIGITAL SIGNAL BOOSTER.VHF 136-174MHz, +24dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 2MHz BW internal Duplexer Serving side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-V3SL: DIGITAL SIGNAL BOOSTER.VHF 136-174MHz, +24dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 3.5MHz BW internal Duplexer Serving side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VNH: DIGITAL SIGNAL BOOSTER.VHF 136-174 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, No internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-V3H: DIGITAL SIGNAL BOOSTER.VHF 136-174 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, VHF: 3.5MHz BW internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VUN4H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, VHF: No Internal Duplexer, UHF: Band#1 Broadband Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VUN04H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, VHF: No Internal Duplexer, UHF: Band#1 Narrow Filter Band#2: Broadband Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VUNMDAH: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, VHF: No Internal Duplexer, UHF: 453-454/458-459 & 460-462/465-467MHz internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VUT3NH: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, VHF: 3.5MHz BW Internal Duplexer, UHF: No Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VU34H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, VHF: 3.5MHz BW Internal Duplexer, UHF: Band#1 Broadband Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VU304H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, VHF: 3.5MHz BW Internal Duplexer, UHF: Band#1 Narrow Filter Band#2: Broadband Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VU3MDAH: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, VHF: 3.5MHz BW Internal Duplexer, UHF: 453-454/458-459 & 460-462/465-467MHz internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VUTNNH: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz, VHF:+30dBm UHF:+37dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, VHF: No Internal Duplexer, UHF: No Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VTN0H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, VHF: No Internal Duplexer, UHF: Band#1 Narrow Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VTN00H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, VHF: No Internal Duplexer, UHF: Band#1 Narrow Filter Band#2: Narrow Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VTNRWCH: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, VHF: No Internal Duplexer, UHF: 483.4-484.5/486.4-487.5 & 488.5-489/491.5-492MHz internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VT30H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, VHF: 3.5MHz BW Internal Duplexer, UHF: Band#1 Narrow Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VT300H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, VHF: 3.5MHz BW Internal Duplexer, UHF: Band#1 Narrow Filter Band#2: Narrow Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-VT3RWCH: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, VHF: 3.5MHz BW Internal Duplexer, UHF: 483.4-484.5/486.4-487.5 & 488.5-489/491.5-492MHz internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-U4H: DIGITAL SIGNAL BOOSTER.UHF 450-512 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC, Band#1: Broadband Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-UMDAH: DIGITAL SIGNAL BOOSTER.UHF 453-454/458-459 & 460-462/465-467 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC, Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-U04H: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-512 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC, Band#1: Narrow Filter - Band #2: Broadband Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-UTNH: DIGITAL SIGNAL BOOSTER. UHF 450-512MHz, +37dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, No Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-UTMDA0H: DIGITAL SIGNAL BOOSTER TRIPLE SUB BAND.UHF 450-512 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC, Band#1: 453-454/458-459MHz - Band #2: 460-462/465-467MHz - Band #3: Narrow Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-T0H: DIGITAL SIGNAL BOOSTER.UHF 450-512 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC, Band#1: Narrow Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-T00H: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-512 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC, Band#1: Narrow Filter - Band #2: Narrow Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-TRWCH: DIGITAL SIGNAL BOOSTER.UHF 483.4-484.5/486.4-487.5 & 488.5-489/491.5-492 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC, Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-TWMOH: DIGITAL SIGNAL BOOSTER.UHF 489.5-491/492.5-494 & 496.3-497/499.3-500 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC, Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-A-T000L: DIGITAL SIGNAL BOOSTER TRIPLE SUB BAND.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: Narrow Filter - Band #2: Narrow Filter - Band #3: Narrow Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL BDA

HONBDA-D-T00H: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-512 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, DC, Band#1: Narrow Filter - Band #2: Narrow Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-D-T0H: DIGITAL SIGNAL BOOSTER.UHF 450-512 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, DC, Band#1: Narrow Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-D-TRWCH: DIGITAL SIGNAL BOOSTER.UHF 483.4-484.5/486.4-487.5 & 488.5-489/491.5-492 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, DC, Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL BDA

HONBDA-D-TWMOH: DIGITAL SIGNAL BOOSTER.UHF 489.5-491/492.5-494 & 496.3-497/499.3-500 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, DC, Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL BDA

HONBDA-D-U04H: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-512 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, DC, Band#1: Narrow Filter - Band #2: Broadband Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-D-U4H: DIGITAL SIGNAL BOOSTER.UHF 450-512 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, DC, Band#1: Narrow Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-D-UMDAH: DIGITAL SIGNAL BOOSTER.UHF 453-454/458-459 & 460-462/465-467 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, DC, Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL BDA

HONBDA-D-UTMDA0H: DIGITAL SIGNAL BOOSTER TRIPLE SUB BAND.UHF 450-512 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, DC, Band#1: 453-454/458-459MHz - Band #2: 460-462/465-467MHz - Band #3: Narrow Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-D-UTNH: DIGITAL SIGNAL BOOSTER.UHF 450-512 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, DC, No internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL BDA

HONBDA-D-VT300H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, DC, VHF: 3.5MHz BW Internal Duplexer, UHF: Band#1 Narrow Filter Band#2: Narrow Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-D-VT30H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, DC, VHF: 3.5MHz BW Internal Duplexer, UHF: Band#1 Narrow Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-D-VT3RWCH: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 483.4-484.5/486.4-487.5 & 488.5-489/491.5-492MHz internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL BDA

HONBDA-D-VTN00H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, DC, VHF: No Internal Duplexer, UHF: Band#1 Narrow Filter Band#2: Narrow Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-D-VTN0H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, DC, VHF: No Internal Duplexer, UHF: Band#1 Narrow Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-D-VTNRWCH: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, DC, VHF: No Internal Duplexer, UHF: 483.4-484.5/486.4-487.5 & 488.5-489/491.5-492MHz internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL BDA

HONBDA-D-VU304H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, DC, VHF: 3.5MHz BW Internal Duplexer, UHF: Band#1 Narrow Filter Band#2: Broadband Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-D-VU34H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, DC, VHF: 3.5MHz BW Internal Duplexer, UHF: Band#1 Broadband Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-D-VU3MDAH: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 453-454/458-459 & 460-462/465-467MHz internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL BDA

HONBDA-D-VUN04H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, DC, VHF: No Internal Duplexer, UHF: Band#1 Narrow Filter Band#2: Broadband Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-D-VUN4H: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, DC, VHF: No Internal Duplexer, UHF: Band#1 Broadband Filter Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-D-VUNMDAH: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, DC, VHF: No Internal Duplexer, UHF: 453-454/458-459 & 460-462/465-467MHz internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL BDA

HONBDA-A-VUN2DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 2MHz BW Internal Duplexer, Donor Side only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUN4DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136--174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 4MHz BW Internal Duplexer, Donor Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUN5DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF : No Internal Duplexer, UHF: 5MHz BW Internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUN04DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: DUAL SUB BAND, Band #1: 0.7MHz BW, Band #2: 4MHz BW, internal Duplexer, Donor,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUN22DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: DUAL SUB BAND, Each Band 2MHz BW, internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUNMDADL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 453-454/458-459 & 460-462/465-467MHz internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUT2NDL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2MHz BW Internal Duplexer, UHF: No Internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU22DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2MHz BW Internal Duplexer, UHF: 2MHz BW Internal Duplexer, Donor Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU24DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2MHz BW Internal Duplexer, UHF: 4MHz BW Internal Duplexer, UHF: 4MHz BW Internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-D-VUT3NH: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, DC, VHF: 3.5MHz BW Internal Duplexer, UHF: No Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL Digital BDA

HONBDA-D-VUTNNH: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +30dBm, UHF: +37dBm, 32filters + 2 Adj sub band per Band, NFPA, DC, VHF: No Internal Duplexer, UHF: No Internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL BDA

HONBDA-A-T000H: DIGITAL SIGNAL BOOSTER TRIPLE SUB BAND.UHF 450-512 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC, Band#1: Narrow Filter - Band #2: Narrow Filter - Band #3: Narrow Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL BDA

HONBDA-D-T000H: DIGITAL SIGNAL BOOSTER TRIPLE SUB BAND.UHF 450-512 MHz, +37dBm, 32 filters +2 Adj sub bands, NFPA, class A, DC, Band#1: Narrow Filter - Band #2: Narrow Filter - Band #3: Narrow Filter, internal Duplexer ,UL2524 2nd Edition Listed FIPLEX BY HONEYWELL BDA

HONBDA-A-VU25DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2MHz BW Internal Duplexer, UHF: 5MHz BW Internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU204DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Band #1: 0.7MHz BW, Band #2: 4MHz BW, internal Duplexer, D, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU222DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Each Band 2MHz BW, internal Duplexer, Donor Side only,UL2524

2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU2MDADL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2MHz BW Internal Duplexer, UHF: 453-454/458-459 & 460-462/465-467MHz internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUT3NDL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer UHF: No Internal Duplexer, Donor Side only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU32DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 2MHz BW Internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU34DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 4MHz BW Internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU35DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 5MHz BW Internal Duplexer, Donor Side only UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU304DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Band #1: 0.7MHz BW, Band #2: 4MHz BW, internal Duplexer ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU322DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Each Band 2MHz BW, internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU3MDADL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 453-454/458-459 & 460-462/465-467MHz internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUN2SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 2MHz BW Internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUN4SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 4MHz BW Internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUN5SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 5MHz BW Internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUN04SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: DUAL SUB BAND, Band #1: 0.7MHz BW, Band #2: 4MHz BW, internal Duplexer, Serving,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUN22SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: DUAL SUB BAND, Each Band 2MHz BW, internal Duplexer, Serving Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUNMDASL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No InternalDuplexer, UHF: 453-454/458-459 & 460-462/465-467MHz internal Duplexer, Serving Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUT2NSL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2MHz BW Internal Duplexer, UHF: No Internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU22SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2MHz BW Internal Duplexer, UHF: 2MHz BW Internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU24SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2MHz BW Internal Duplexer, UHF: 4MHz BW Internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU25SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2MHz BW Internal Duplexer, UHF: 5MHz BW Internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU204SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Band #1: 0.7MHz BW, Band #2: 4MHz BW, internal Duplexer,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU222SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Each Band 2MHz BW, internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU2MDASL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2MHz BW Internal Duplexer, UHF: 453-454/458-459 & 460-462/465-467MHz internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUT3NSL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: No Internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU32SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 2MHz BW Internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU34SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 4MHz BW Internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU35SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adjsub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 5MHz BW Internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU304SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Band #1: 0.7MHz BW, Band #2: 4MHz BW, internal Duplexer, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU322SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Each Band 2MHz BW, internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VU3MDASL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 453-454/458-459 & 460-462/465-467MHz internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUT202L: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Band #1: 2.0MHz BW, Band #2: 0.7MHz BW, internal Duplexer UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VUTN02L: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 450-470MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No internal Duplexer, UHF: DUAL SUB BAND, Band #1: 2.0MHz BW, Band #2: 0.7MHz BW, internal Duplexer, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT301L: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC, VHF: 3.5MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Band 1: 1.5MHz BW, Band #2: 0.7MHz, internal Duplexer, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VTN0DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 0.7MHz BW Internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VTN1DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 1.5MHz BW Internal Duplexer, Donor Side only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VTN2DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 2MHz BW Internal Duplexer, Donor Side only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VTN00DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: DUAL SUB BAND, Each Band 0.7MHz BW, internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VTN11DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: DUAL SUB BAND, Each Band 1.5MHz BW, internal Duplexer, Donor Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VTNRWCDL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 483.4-484.5/ 486.4-487.5 & 488.5-489/491.5-492MHz internal Duplexer, DonorSide,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT20DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2.0MHz BW Internal Duplexer, UHF: 0.7MHz BW Internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT21DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2.0MHz BW Internal Duplexer, UHF: 1.5MHz BW Internal Duplexer, Donor Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT22DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2.0MHz BW Internal Duplexer, UHF: 2MHz BW Internal Duplexer, Donor Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT200DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2.0MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Each Band 0.7MHz BW, internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT211DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2.0MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Each Band 1.5MHz BW, internal Duplexer, Donor Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT2RWCDL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2.0MHz BW Internal Duplexer, UHF: 483.4-484.5/486.4-487.5 & 488.5-489/491.5-492MHz internal Duplexer, Donor,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT30DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 0.7MHz BW Internal Duplexer, Donor Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT31DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 1.5MHz BW Internal Duplexer, Donor Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT32DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 2MHz BW Internal Duplexer, Donor Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT300DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Each Band 0.7MHz BW, internal Duplexer, Donor Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT311DL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Each Band 1.5MHz BW, internal Duplexer, Dono Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT3RWCDL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 483.4-484.5/486.4-487.5 & 488.5-489/491.5-492MHz internal Duplexer, Donor, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VTN0SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filter + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 0.7MHz BW Internal Duplexer, Serving Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VTN1SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 1.5MHz BW Internal Duplexer, Serving Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VTN2SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 2MHz BW Internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VTN00SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: DUAL SUB BAND, Each Band 0.7MHz BW, internal Duplexer, Serving Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VTN11SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: DUAL SUB BAND, Each Band 1.5MHz BW, internal Duplexer, Serving Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VTNRWCSL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: No Internal Duplexer, UHF: 483.4-484.5/ 486.4-487.5 & 488.5-489/491.5-492MHz internal Duplexer, Serving Side,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT20SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2.0MHz BW Internal Duplexer, UHF: 0.7MHz BW Internal Duplexer, Serving Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT21SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2.0MHz BW Internal Duplexer, UHF: 1.5MHz BW Internal Duplexer, Serving Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT22SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2.0MHz BW Internal Duplexer, UHF: 2MHz BW Internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT200SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2.0MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Each Band 0.7MHz BW, internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT211SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2.0MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Each Band 1.5MHz BW, internal Duplexer, Serving Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT2RWCSL: DIGITAL SIGNAL BOOSTER DUAL BAND.VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 2.0MHz BW Internal Duplexer, UHF: 483.4-484.5/486.4-487.5 & 488.5-489/491.5-492MHz internal Duplexer, Serving,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT30SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz& UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 0.7MHz BW Internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT31SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 1.5MHz BW Internal Duplexer, Serving Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT32SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 2MHz BW Internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT300SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Each Band 0.7MHz BW, internal Duplexer, Serving Side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT311SL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: DUAL SUB BAND, Each Band 1.5MHz BW, internal Duplexer, Serving Side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-VT3RWCSL: DIGITAL SIGNAL BOOSTER DUAL BAND. VHF 136-174MHz & UHF 470-512MHz. VHF: +24dBm, UHF: +30dBm, 32filters + 2 Adj sub band per Band, NFPA, AC & DC, VHF: 3.5MHz BW Internal Duplexer, UHF: 483.4-484.5/486.4-487.5 & 488.5-489/491.5-492MHz internal Duplexer,Serv,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-U5L: DIGITAL SIGNAL BOOSTER.UHF 450-470 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 5MHz BW internal Duplexer,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-U2DL: DIGITAL SIGNAL BOOSTER.UHF 450-470 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 2MHz BW internal Duplexer Donor side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-U4DL: DIGITAL SIGNAL BOOSTER.UHF 450-470 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 4MHz BW internal Duplexer Donor side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-U24DL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450- 470 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC&DC, Band #1: 2MHz BWW, Band #2: 4MHz BW internal Duplexer Donor Side Only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-U24SL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-470 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC&DC, Band #1: 2MHz BWW, Band #2: 4MHz BW internal Duplexer Serving Side Only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-U5DL: DIGITAL SIGNAL BOOSTER.UHF 450-470 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 5MHz BW internal Duplexer Donor side only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-U2SL: DIGITAL SIGNAL BOOSTER.UHF 450-470 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 2MHz BW internal Duplexer Serving side only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-U4SL: DIGITAL SIGNAL BOOSTER.UHF 450-470 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 4MHz BW internal Duplexer Serving side only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-U5SL: DIGITAL SIGNAL BOOSTER.UHF 450-470 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 5MHz BW internal Duplexer Service side only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-UMDADL: DIGITAL SIGNAL BOOSTER.UHF 453-454/458-459 & 460-462/465-467 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Internal Duplexer Donor side only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-UMDASL: DIGITAL SIGNAL BOOSTER.UHF 453-454/458-459 & 460-462/465-467 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Internal Duplexer Serving side only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-U22DL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-470 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 2.0MHz BW - Band #2: 2.0MHz BW, internal Duplexer, Donor Side Only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-U04DL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-470 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 0.7MHz BW - Band #2: 4.0MHz BW, internal Duplexer, Donor Side Only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-U22SL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-470 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 2.0MHz BW - Band #2: 2.0MHz BW, internal Duplexer, Serving Side Only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-U04SL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-470 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 0.7MHz BW - Band #2: 4.0MHz BW, internal Duplexer, Serving Side Only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-UT012L: DIGITAL SIGNAL BOOSTER TRIPLE SUB BAND.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 2.0MHz BW - Band #2: 1.5MHz BW - Band #3: 0.7MHz BW, internal Duplexer,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-UT02DL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 2.0MHz BW - Band #2: 0.7MHz BW, internal Duplexer, Donor Side Only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-UT12DL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 2.0MHz BW - Band #2: 1.5MHz BW, internal Duplexer, Donor Side Only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-UT22DL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 2.0MHz BW - Band #2: 2.0MHz BW, internal Duplexer, Donor Side Only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-UT002DL: DIGITAL SIGNAL BOOSTER TRIPLE SUB BAND.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 2.0MHz BW - Band #2: 0.7MHz BW - Band #3: 0.7MHz BW, internal Duplexer, Donor Side Only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-UTMDA0DL: DIGITAL SIGNAL BOOSTER TRIPLE SUB BAND.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 453-454/458-459MHz - Band #2: 460-462/465-467MHz - Band #3: 0.7MHz BW, internal Duplexer, Donor Side Only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-UT02SL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 2.0MHz BW - Band #2: 0.7MHz BW, internal Duplexer, Serving Side Only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-UT12SL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 2.0MHz BW - Band #2: 1.5MHz BW, internal Duplexer, Serving Side Only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-UT22SL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 2.0MHz BW - Band #2: 2.0MHz BW, internal Duplexer, Serving Side Only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-UT002SL: DIGITAL SIGNAL BOOSTER TRIPLE SUBAND.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC& Band#1: 2.0MHz BW - Band #2: 0.7MHz BW - Band #3: 0.7MHz BW, internal Duplexer, Serving Side Only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-UTMDA0SL: DIGITAL SIGNAL BOOSTER TRIPLE SUB BAND.UHF 450-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC,Band#1: 453-454/458-459MHz - Band #2: 460-462/465-467MHz - Band #3: 0.7MHz BW, internal Duplexer, Serving Side Only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T0DL: DIGITAL SIGNAL BOOSTER.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 0.7MHz BW internal Duplexer Donor side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T1DL: DIGITAL SIGNAL BOOSTER.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 1.5MHz BW internal Duplexer Donor side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T2DL: DIGITAL SIGNAL BOOSTER.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 2MHz BW internal Duplexer Donor side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T0SL: DIGITAL SIGNAL BOOSTER.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 0.7MHz BW internal Duplexer Serving side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T1SL: DIGITAL SIGNAL BOOSTER.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 1.5MHz BW internal Duplexer Serving side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T2SL: DIGITAL SIGNAL BOOSTER.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, 2MHz BW internal Duplexer Serving side only,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T000L: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 0.7MHz BW - Band #2: 0.7MHz BW - Band #3: 0.7MHz BW, internal Duplexer,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T001L: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 0.7MHz BW - Band #2: 0.7MHz BW - Band #3: 1.5MHz BW, internal Duplexer,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T011L: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 0.7MHz BW - Band #2: 1.5MHz BW - Band #3: 1.5MHz BW, internal Duplexer ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T111L: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1

1.5MHz BW - Band #2: 1.5MHz BW - Band #3: 1.5MHz BW, internal Duplexer ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T00DL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 0.7MHz BW - Band #2: 0.7MHz BW, internal Duplexer, Donor Side Only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T01DL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 0.7MHz BW - Band #2: 1.5MHz BW, internal Duplexer, Donor Side Only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T11DL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 1.5MHz BW - Band #2: 1.5MHz BW, internal Duplexer, Donor Side Only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T12DL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 2.0MHz BW - Band #2: 1.5MHz BW, internal Duplexer, Donor Side Only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T00SL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 0.7MHz BW - Band #2: 0.7MHz BW, internal Duplexer, Serving Side Only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T01SL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC& DC, Band#1: 0.7MHz BW - Band #2: 1.5MHz BW, internal Duplexer, Serving Side Only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T11SL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 470-512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC,Band#1: 1.5MHz BW - Band #2: 1.5MHz BW, internal Duplexer, Serving side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-T12SL: DIGITAL SIGNAL BOOSTER DUAL SUB BAND.UHF 470- 512 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Band#1: 2.0MHz BW - Band #2: 1.5MHz BW, internal Duplexer, Serving Side Only ,UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-TRWCDL: DIGITAL SIGNAL BOOSTER.UHF 483.4-484.5/486.4- 487.5 & 488.5-489/491.5-492 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Internal Duplexer Donor side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-TRWCSL: DIGITAL SIGNAL BOOSTER.UHF 483.4-48s4.5/486.4-487.5 & 488.5-489/491.5-492 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Internal Duplexer Serving side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-TWMODL: DIGITAL SIGNAL BOOSTER.UHF 489.5-491/492.5- 494 & 496.3-497/499.3-500 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Internal Duplexer Donor side only, UL2524 2nd Edition Listed HONEYWELL BDA

HONBDA-A-TWMOSL: DIGITAL SIGNAL BOOSTER.UHF 489.5-491/492.5- 494 & 496.3-497/499.3-500 MHz, +30dBm, 32 filters +2 Adj sub bands, NFPA, class A, AC & DC, Internal Duplexer Serving side only, UL2524 2nd Edition Listed HONEYWELL BDA

Standards and Codes

The HONBDA units comply with the following Standards and Codes.

- Buy American Compliant: Meets the definition of Domestic Construction Material under the Buy American Act
- FCC (Federal Communications Commission-US)
- Industrial Canada (IC) Compliant
- IFC 2015, 2018, 2021 Edition Standard
- ISO 9001 Compliant
- NFPA 72 2013 Edition, NFPA 1221 2016 2019 Edition, and NFPA 1225 2022 Edition Standard
- RoHS Compliant
- UL2524 3rd Edition Listing with SGS, Nationally Recognized Testing Laboratory (NRTL) approved by OSHA for UL2524.

This document is not intended to be used for installation purposes.
We try to keep our product information up-to-date and accurate.
We cannot cover all specific applications or anticipate all requirements.
All specifications are subject to change without notice.

Fiplex™ is a trademark of Fiplex Communications, Inc.
FirstNet™ is a trademark of the U.S. Dept. of Commerce.
©2025 by Honeywell International Inc. All rights reserved.
Unauthorized use of this document is strictly prohibited.