HPF24S6 and HPF24S8

Power Supplies with Battery Chargers

Description

The HPF24S6 and HPF24S8 are compact, cost-effective, 6 amp. or 8 amp. remote power supplies with integral battery chargers. These adaptable power supplies may be connected to any 12 or 24 volt Fire Alarm Control Panel (FACP) or the power supplies may stand-alone. Primary applications include the following:

- Notification Appliance Circuits (NAC) expansion to support ADA requirements and NAC synchronization
- Auxiliary power to support 24 volt system accessories

These power supplies provide regulated and filtered 24 VDC power to four (4), notification appliance circuits, configured as either four (4), Class B (Style Y) or Class A (Style A, with ZNAC-4 Option Module). Alternately, the four outputs may be configured as follows:

- all non-resettable
- all resettable
- two non-resettable
- two resettable

The power supplies also contain a battery charger with a charging capacity of up to 18 Amp Hour batteries.

The HPF24S6 and HPF24S8 power supplies comply with the following Agency standards:

- NFPA 72 National Fire Alarm Code,
- UL Standard 864, 9th Edition for control units for Fire Alarm Systems (NAC expander mode).
- UL 1481 Power Supplies for Fire Alarm Systems (stand-alone mode).



HFP24S6/8 dh1061.jpg

Features

- UL® Listed NAC synchronization using System Sensor, Cooper-Wheelock or Gentex (Commander Series) appliances
- Uses a cascade of up to ten (10), power supplies or (four (4), power supplies with Gentex) with strobe timing maintained
- Operates as a sync follower or a sync generator (default)
- Contains two (2), fully -isolated input/control circuits energized from FACP notification appliance circuit (NAC expander mode) or jumpered permanently on (stand-alone mode)
- Configured to internally house an addressable SLC control module for alarm activation
- Supports four (4), Class B (Style Y) or four (4), Class A (Style Z) (with ZNAC-4 Module) notification appliance circuits
- Provides 6.0A or 8.0A (depending on model) full load output (3.0A maximum per circuit) in NAC expander mode (UL Standard 864)
- Uses 4.0A or 6.0A continuous output in the stand-alone mode (UL Standard 1481)

SIGNALING
LISTED
S6677
S6677
7315-1637:0102

UL® is a registered trademark for Underwriter's Laboratories Inc.

GAMEWELL-FCI
12 Clintonville Road, Northford, CT 06472-1610 USA • Tel: (203) 484-7161 • Fax: (203) 484-7118
Specifications are for information only, are not intended for installation purposes, and are subject to change without notice. No responsibility is assumed by Gamewell-FCI for their use.
©2013 by Honeywell International Inc. All rights reserved.

Features (Continued)

- In stand-alone mode, output power circuits are configured as resettable, (using the FACP reset switch), non-resettable, or a combination of both
- Fully regulated and filtered power output (optimal for powering four-wire smoke detectors, annunciators and other system peripherals requiring regulated/filtered power)
- Class 2 Power-Limited technology complies with UL Class 2 Power-Limited requirements
- Includes a normally-closed trouble relay
- Provides fully, supervised power supply, battery and notification appliance circuits
- Selectable earth fault detection
- AC trouble report selectable for immediate or up to an 8 hour delay
- Compatible with any UL Standard 864 fire alarm control panel which uses an industry standard, reverse polarity, and notification circuit (including unfiltered and unregulated bell power)
- Requires input trigger voltage of 9.0 -32 VDC
- Built with a self-contained compact, lockable cabinet 15” H x 14.5” W x 2.75” D (38.1 H x 36.8 W x 7.0 D cm)
- Includes an integral battery charger capable of charging up to 18 AH batteries. The cabinet has the capacity of housing 7.0 AH batteries
- Battery charger may be disabled via a DIP (Dual In-Line Package) switch for applications requiring larger batteries
- Offers fixed, clamp-type terminal blocks that accommodate up to 12 AWG (3.1 mm^2) wire

Specifications

Primary (AC) Power

- HPF24S6: 120 VAC 60 Hz, 3.2A maximum
- HPF24S8: 120 VAC 60 Hz, 3.2A maximum
- Wire size: minimum 14 AWG (2.0 mm²) with 600V insulation

Control Input Circuit

- Input Voltage: 9.0 to 32 VDC
- Input Current: 2.0 mA (16 - 32 V) per input 1.0 mA (9 - 16 V)

Trouble Contact Rating

- 5.0A at 24 VDC

Auxiliary Power Output

- Specific Application Power - 500 mA maximum

Output Circuits

- +24 VDC filtered, regulated
- 3.0A maximum for any one circuit

Specifications (Continued)

Output Circuits (Continued)

- 4.0A maximum total continuous current for all outputs (Stand-alone mode) for the HPF24S6 and 6A for the HPF24S8
- 6A or 8A, depending on the model, maximum total short-term current for all outputs (NAC Expander mode).

Secondary Power (Battery) Charging Circuit

- Supports lead-acid batteries only
- Float Charge Voltage: 27.6 VDC
- Maximum Charge Current: 1.5A
- Maximum Battery Capacity: 18 AH

Ordering Information

Part Number	Description
HPF24S6	Remote charger 6A power supply (120 VAC). Includes the main printed circuit board, transformers, red enclosure, and installation instructions
HPF24S8	Remote charger 8A power supply (120 VAC). Includes the main printed circuit board, transformers, red enclosure, and installation instructions
FCPS-24S6RB	Replacement mother board
ZNAC-4 -	Class A (Style Z) NAC option module
BAT-1270 -	Battery, 12 volt, 7.0 AH (two required)