

IFP-300ECS SERIES

Intelligent Fire Alarm Control Panel with Emergency Communication System

The IFP-300ECS Series panels and accessories provide features to meet the requirements for Mass Notification Systems as described in UL 2572 2nd Edition and UL 864 10th Edition.

The IFP-300ECS (red) and IFP-300ECSB (black) are intelligent addressable Fire Alarm Control Panels combined with an Emergency Communication System (ECS) and are direct replacements for the IFP-100ECS FACP. When the ECS features are enabled, they are integrated with the fire alarm and voice evacuation functions of the control panel.

The emergency communication system operations include an onboard supervised microphone. All-call and Non-active call buttons can quickly select all active or non-active output groups. The system also allows for emergency messages over fire.

The IFP-300ECS FACPs have one built-in signaling line circuit (SLC), which can support 159 IDP (Intelligent Device Protocol) or SK detectors and 159 IDP or SK modules, or 127 SD protocol devices. Additional SLC loops can be added for a maximum of 300 (IDP/SK) or 254 (SD) points per panel.

The built-in digital alarm communicator/transmitter (DACT) is dual technology, IP and POTS. The POTS transmits system status (alarms, troubles, AC loss, etc.) to a Central Station via the public switched telephone network. The IP communicator's internet monitoring capability sends alarm signals over the Internet saving the monthly cost of two dedicated business telephone lines. Although not required, the secondary telephone line may be retained providing backup communication over the public switched telephone line. Optional cellular reporting is available.

The IFP-300ECS has four onboard Flexput® circuits that can be configured as notification outputs or auxiliary power. The IFP-300ECS also has a form-C trouble relay, and two programmable form-C relays, along with powerful features such as drift compensation, pre-trouble maintenance alert, a built-in sensor test to comply with NFPA 72 calibration testing requirements, and a calibration trouble alert.

The IFP-300ECS has interconnection capability for up to 32 panels. The system has two modes of operation, multiple panels covering one larger building, or multiple independent buildings.



FEATURES AND BENEFITS

- Single enclosure for both fire and emergency control components
- Ability to select ECS messages as priority over fire
- 15 Recordable one-minute messages that can be mapped to eight ECS buttons
- Capable of producing 520 Hz tones to meet NFPA 72 requirements
- Support for up to 15 LOC consoles and 16 addressable amplifiers
- Expandable SLC loops to 300 (IDP/SK) or 254 (SD) point capacity
- Four Flexput circuits for NAC outputs or auxiliary power
- Selectable strobe synchronization for Amseco®, System Sensor®, Wheelock®, and Gentex® devices
- Built-in DACT with IP and optional cellular reporting
- Built-in USB interface for quick and easy programming
- JumpStart® auto programming reduces installation time
- 250 software zones & 250 output groups for flexible design options
- 23 preset notification cadence patterns (including ANSI® 3.41)
- Allows up to 24 SBUS devices
- Four programmable function keys
- Two programmable relays and one fixed trouble relay
- Compatible with SWIFT® wireless devices
- Convenient field-upgradeable firmware
- Network support for up to 32 sites
- Network card allows copper network connection with a multi-mode or single-mode fiber connection
- Real-time clock/calendar with automatic daylight savings control
- History file with 1,000 event capacity

Honeywell

Farenhty Series

USER INTERFACE

LED INDICATORS

- General Alarm (Red)
- Supervisory (Yellow)
- System Trouble (Yellow)
- System Silenced (Yellow)
- System Power (Green)

KEYPAD

- 12-key numeric pad
- Acknowledge
- Alarm Silence
- System Reset
- Drill
- F1-F4 Programmable Function Keys

PROGRAMMING

The IFP-300ECS system offers several options to simplify and expedite programming. JumpStart® auto programming minimizes programming required to start a new system. The built-in keypad, or the remote annunciators give on-site access to current system programming. System programming can also be accomplished using the Windows®-based Honeywell Fire Software Suite (HFSS).

ORDERING INFORMATION

IFP-300ECS: Addressable fire alarm control panel with emergency communication system, red

IFP-300ECSB: Addressable fire alarm control panel with emergency communication system, black

COMPATIBLE ECS EQUIPMENT

ECS-50W: 50 Watt amplifier

ECS-50WB: 50 Watt amplifier, black

ECS-125W: 125 Watt amplifier

ECS-125WB: 125 Watt amplifier, black

ECS-DUAL50W: 50 Watt dual amplifier

ECS-DUAL50WB: 50 Watt dual amplifier, Black

ECS-INT50W: 50 /Watt internal amplifier

ECS-50WBU: External backup amplifier

ECS-CE4: Provides 4 additional audio circuits

ECS-RVM: Remote voice module

ECS-SW24: 24 switch expander

ECS-VCM: Voice control module

ECS-NVCM: Network voice control module

ECS-LOC: Local operator console

ECS-LOCB: Local operator console, black

ECS-LOC2100: Local operators console, red

ECS-LOC2100B: Local operator console, black

ECS-RPU: Remote paging unit. red

COMPATIBLE SBUS DEVICES

RA-2000: 4x40 LCD remote fire annunciator with four programmable buttons, red

RA-2000GRAY: 4x40 LCD remote fire annunciator with four programmable buttons, gray

RA-1000: 4x20 LCD remote fire annunciator, gray

RA-1000R: 4x20 LCD remote fire annunciator, red

RA-100: 4x20 LCD remote fire annunciator, red

5865-3: LED annunciators- display up to 30 LEDs (15 red/15 yellow)

5865-4: LED annunciators- display up to 30 LEDs (15 red/15 yellow). Key switches for silence and reset, and a system trouble LED

5880: LED I/O module with 40 programmable LED outputs and eight supervised dry contact inputs

5883: Relay interface. Provides 10 Form C relays

5824: Serial/Parallel printer interface module for printer connection

SK COMPATIBLE ADDRESSABLE DEVICES

Note: SK and SD devices cannot be mixed in the same fire alarm system.

SK-ACCLIMATE: Multi criteria photoelectric smoke detector with thermal 135°F fixed temperature

SK-BEAM: Reflected beam smoke detector without test feature

SK-BEAM-T: Reflected beam smoke detector with test feature

OSI-RI-SK: Reflected beam smoke detector, SK protocol

SK-CONTROL: Supervised control module

SK-CONTROL-6: Six circuit supervised control module

SK-DUCT: Photoelectric duct smoke detector with extended air speed range

SK-FIRE-CO: Four criteria fire and carbon monoxide detector

SK-FIRE-CO-W: Four criteria fire and carbon monoxide detector, white

SK-HEAT: Fixed thermal detector (135°F)

SK-HEAT-W: Fixed thermal detector (135°F), white

SK-HEAT-ROR: Fixed rate of rise detector

SK-HEAT-HT: Fixed high temperature heat detector (190°F)

SK-HEAT-HT-W: Fixed high temperature heat detector (190°F), white

SK-HEAT-ROR-W: Fixed rate of rise detector, white

SK-ISO: Fault isolator module

SK-MINIMON: Mini monitor module

SK-MONITOR: Monitor module

SK-MONITOR-2: Dual input monitor module

SK-MON-10: 10- input monitor module

SK-PHOTO: Photoelectric smoke detector

SK-PHOTO-W: Photoelectric smoke detector, white

SK-PHOTO-R: Photoelectric detector with remote test capability

SK-PHOTO-R-W: Photoelectric detector with remote test capability, white

SK-PHOTO-T: Photoelectric smoke detector with fixed heat (135°F)

SK-PHOTO-T-W: Photoelectric smoke detector with fixed thermal heat (135°F), white
SK-PTIR-W: Multi criteria photoelectric smoke detector with thermal 135°F fixed temperature, white
SK-PULL-SA: Addressable single action pull station
SK-PULL-DA: Addressable dual action pull station
SK-RELAY: Addressable relay module
SK-RELAY-6: Addressable Six relay control module
SK-RELAYMON-2: Addressable Dual relay/monitor module
SK-ZONE: Addressable zone interface module
SK-ZONE-6: Six zone interface module

IDP COMPATIBLE ADDRESSABLE DEVICES

IDP and SD devices cannot be mixed in the same fire alarm system.

IDP-ACCLIMATE: Multi criteria photoelectric smoke detector with thermal 135°F fixed temperature
IDP-BEAM: Reflected beam smoke detector without test feature
IDP-BEAM-T: Reflected beam smoke detector with test feature
OSI-RI-IDP: Reflected beam smoke detector, IDP protocol
IDP-CONTROL: Supervised control module
IDP-CONTROL-6: Six circuit supervised control module
IDP-DUCT: Photoelectric duct smoke detector with extended air speed range
IDP-FIRE-CO: Four criteria fire and carbon monoxide detector
IDP-FIRE-CO-W: Four criteria fire/carbon monoxide detector, white
IDP-FIRE-CO-IV: Four criteria fire/carbon monoxide detector, ivory
IDP-HEAT: Fixed thermal detector (135°F)
IDP-HEAT-W: Fixed thermal detector (135°F), white
IDP-HEAT-IV: Fixed thermal detector (135°F), ivory
IDP-HEAT-ROR: Fixed rate of rise detector
IDP-HEAT-HT: Fixed high temp thermal detector (190°F)
IDP-HEAT-HT-W: Fixed high temp thermal detector (190°F), white
IDP-HEAT-HT-IV: Fixed high temp thermal detector (190°F), ivory
IDP-HEAT-ROR-W: Fixed rate of rise detector, white
IDP-HEAT-ROR-IV: Fixed rate of rise detector, ivory
IDP-ISO: Fault isolator module
IDP-MINIMON: Mini monitor module
IDP-MONITOR: Monitor module
IDP-MONITOR-2: Dual input monitor module
IDP-MON-10: 10- input monitor module
IDP-PHOTO: Photoelectric smoke detector
IDP-PHOTO-W: Photoelectric smoke detector, white
IDP-PHOTO-IV: Photoelectric smoke detector, ivory
IDP-PHOTO-R: Photoelectric detector with remote test capability
IDP-PHOTO-R-W: Photoelectric detector with remote test capability, white
IDP-PHOTO-R-IV: Photoelectric detector with remote test capability, ivory
IDP-PHOTO-T: Photoelectric smoke detector with fixed heat (135°F)

IDP-PHOTO-T-W: Photoelectric smoke detector with fixed heat (135°F), white
IDP-PHOTO-T-IV: Photoelectric smoke detector with fixed thermal heat (135°F), ivory
IDP-PTIR-W: Multi criteria photoelectric smoke detector with thermal 135°F fixed temperature, white
IDP-PTIR-IV: Multi criteria photoelectric smoke detector with thermal 135°F fixed temperature, white
IDP-PULL-SA: Addressable single action pull station
IDP-PULL-DA: Addressable dual action pull station
IDP-RELAY: Addressable relay module
IDP-RELAY-6: Addressable Six relay control module
IDP-RELAYMON-2: Addressable Dual relay/monitor module
IDP-ZONE: Addressable zone interface module
IDP-ZONE-6: Six zone interface module

SK/IDP BASES

B210LP: 6" mounting base
B501: 4" Flangeless mounting base
B200S: Intelligent sounder base
B200S-LF: Low-frequency intelligent sounder base
B224RB: Relay base
B224BI: Isolator base

SD COMPATIBLE ADDRESSABLE DEVICES

Note: SK and SD devices cannot be mixed in the same fire alarm system.

SD505-6AB: Addressable 6" base
SD505-6IB: Addressable 6" short circuit isolator base
SD505-6RB: Addressable 6" relay base
SD505-6SB: Addressable 6" sounder base
SD500-AIM: Addressable input module (switch input)
SD500-ANM: Addressable notification module
SD500-ARM: Addressable relay module
SD505-DTS-K: Remote test switch/LED indicator for the SD505-DUCTR
SD505-DUCT: Addressable Duct Smoke Detector
SD505-DUCTR: Addressable Duct Detector housing with relay base
SD505-HEAT: Absolute temperature heat detector. Trip point range from 135°F–150°F (0°C–37°C)
SD500-LIM: Addressable Line isolator module
SD500-MIM: Addressable Mini input monitor module (switch input)
SD505-PHOTO: Photoelectric smoke detector
SD500-PS/-PSDA: Addressable Single or dual action pull station
SD500-SDM: Addressable smoke detector module

SWIFT WIRELESS DEVICES

Note: SWIFT is only compatible with System Sensor (SK) devices. It is not compatible with Hochiki (SD) devices.

WIDP-WGI: Wireless gateway
WIDP-PHOTO: Wireless photoelectric smoke detector

WIDP-ACCLIMATE: Wireless ACCLIMATE detector
W-SYNC: Wireless sync module
WIDP-HEAT: Wireless, fixed heat detector (135°F)
WIDP-HEAT-ROR: Wireless rate-of-rise heat detector
WIDP-MONITOR: Wireless monitor module
WIDP-RELAY: Wireless relay module
WIDP-PULL-DA: Wireless pull station
B210: Wireless detector base
WAV-RL, WAV-WL, WAV-CRL, WAV-CWL: Wireless AV bases
W-USB: Wireless USB radio/antenna dongle that plugs into the USB port of a PC running SWIFT Tools
SWIFT Tools: Programming and diagnostic utility for the wireless gateway and devices. Available for download from www.farenhyt.com

SYSTEM EXPANDERS

6815: SLC Expander for IDP or SK devices
5815XL: SLC expander for SD devices
RPS-1000: 6A power supply with 6 Flexput circuits & 2 Form C relays
5496: 6 amp NAC power expander with 4 power-limited output ckts

OPTIONAL COMMUNICATORS

HWF2A-COM: Digital Cellular Fire Alarm Communicator and Internet Panel, AT&T
HWF2V-COM: Digital Cellular Fire Alarm Communicator and Internet Panel, Verizon

MISCELLANEOUS ACCESSORIES

SK-NIC: Network Interface Card. Provides a common communications link for the IFP-300
SK-NIC-KIT: Installation Accessory Kit
SK-FML: Fiber-Optic Multi Mode, transmitter and receiver
SK-FSL: Fiber-Optic Single Mode
RBB: Remote battery box accessory cabinet
SK-SCK: Seismic compliance kit used to fasten batteries to the fire panel

SOFTWARE SOLUTIONS

HFSS: Honeywell Fire Software Suite provides remote and local panel programming, detector status, event history and additional data. Databases can be uploaded/downloaded via the panel's USB port using a flash drive. Requires a PC running Microsoft® Windows®.

IFP-300ECS SERIES TECHNICAL SPECIFICATIONS

SYSTEM CAPACITY

Intelligent Signaling Line Circuits: 1 (expandable)

Addressable device capacity: 300 (IDP/SK) or 254 (SD)

Programmable software zones: 250

Output circuits: 4 (expandable)

SBUS devices: 63 (16 annunciators, 8 LED modules)

LOC units: 7

Addressable amplifiers (total watts): 8 (1000)

ELECTRICAL

AC Power: 120 VAC, 60 Hz, 3.25A

Standby Current: 190 mA

Alarm Current: 250 mA

Flexput Circuits: Terminal block provides connections for (four Class B or two Class A) NACs or auxiliary power. Power-limited, supervised circuitry. Maximum current per circuit: 3 A. Cannot exceed 6A total for all circuits. End-of-line resistor: 4.7k ohm, ½ watt for Class B NACs

Communication Loop: Supervised and power-limited, Class A or Class B, 32VDC, 150mA

Two Programmable Relays and One Fixed Trouble Relay: Contact rating: 2.5 A @ 27.4 VDC (resistive), Form C

Battery: Cabinet holds maximum of two 18 AH batteries

Battery Charger Capacity: 17-55 AH

PHYSICAL

Dimensions: 21.6" W x 28.1" H x 5.1" D (54.9cm W x 71.4cm H x 13.0cm D)

Weight: 49 lbs. (22 kg.)

Color: Red or Black

TEMPERATURE AND HUMIDITY RANGES

This system meets NFPA requirements for operation at 0 – 49°C (32– 120°F) and at a relative humidity 93% ± 2% RH (non-condensing) at 32°C ± 2°C (90°F ± 3°F). However, the useful life of the system's standby batteries and the electronic components may be adversely affected by extreme temperature ranges and humidity. Therefore, it is recommended that this system and its peripherals be installed in an environment with a normal room temperature of 15 – 27°C/60 – 80°F.

NFPA STANDARDS

The IFP-300ECS complies with the following standards and codes:

NFPA 72

NFPA 13

NFPA 15

NFPA 16

NFPA 70

UL 864 10th Edition

UL2572 2nd Edition

Central station; remote Signaling; Local Protective Signaling Systems; Auxiliary Protected Premises Unit; Water Deluge releasing service. Suitable for automatic, manual, waterflow, sprinkler supervisory (DACT non-coded) signaling services

AGENCY LISTINGS AND APPROVALS

UL Listed: S2766

CSFM: 7165-0559:0504

FDNY: COA# 6245

FM: Approved

Seismic: (CA) VMA-45894-05C

Farenhyt™ is a trademark, and Flexput®, Honeywell®, JumpStart®, SWIFT®, and System Sensor® are registered trademarks of Honeywell International Inc. Amseco® is a registered trademark of Potter Electric Signal Company, LLC. Gentex® is a registered trademark of Gentex Corporation. Hochiki® is a registered trademark of Hochiki Corporation. Wheelock® is a trademark of Cooper Technologies Company. ANSI® is a registered trademark of the American National Standards Institute, Inc. Microsoft® and Windows® are registered trademarks of Microsoft Corporation.

This document is not intended to be used for installation purposes. We try to keep our product information up-to-date and accurate. We cannot cover all specific applications or anticipate all requirements. All specifications are subject to change without notice.

Country of origin: USA

Honeywell Fire Solutions

12 Clintonville Road
Northford, CT 06472-1610
203.484.7161
www.farenhyt.com

351604 | C | 03/22
©2022 Honeywell International Inc.

THE
FUTURE
IS
WHAT
WE
MAKE IT

Honeywell