

# X-MAP4P

## Digital Multi-audio Player

**Honeywell**



- Two individual USB\SD\BT and AM\FM line output.
- Can play music in two zones at the same time. Mix audio RCA output as well.
- Volume of two line outputs can be adjusted respectively.
- Supports USB high speed、SD Cards, Bluetooth Protocol V4.2.
- Support FLA, WMA, APE, FLAC, WAV, ACC, SBC, MP3 formats.
- AM/FM broadcasting is acceptable, can each save up 60 channels.

### Technical Specifications

|                                  |                                                                                                                                 |
|----------------------------------|---------------------------------------------------------------------------------------------------------------------------------|
| <b>Power supply</b>              | 100-240V AC < 15W 50/60Hz                                                                                                       |
| <b>Input</b>                     | AM/FM 75Ω antenna interface<br>USB port, SD card slot, Bluetooth.                                                               |
| <b>Output</b>                    | Stereo sound RCA output FM/AM tuner (775mV)<br>Stereo sound RCA output USB/SD/BT (775mV)<br>Mix audio RCA output: 775mV         |
| <b>Channels</b>                  | 3                                                                                                                               |
| <b>Unit size</b>                 | 482(W)×44(H)×236(D) mm                                                                                                          |
| <b>Carton size</b>               | 520(W)×120(H)×368(D) mm                                                                                                         |
| <b>Frequency response(dB)</b>    | 20-20KHz ±3dB                                                                                                                   |
| <b>Audio distortion (1 KHz)</b>  | 0.05%                                                                                                                           |
| <b>S/N RATIO(A-WTD)</b>          | ≥80                                                                                                                             |
| <b>Wave band frequency range</b> | FM : 87.0MHz ~ 108MHz, FM : 76.0MHz ~ 90MHz step:0.1MHz<br>AM : 522KHz ~ 1620KHz step:9KHz,<br>AM : 520KHz ~ 1620KHz step:10KHz |

### Honeywell Audiovisuals

No. 257 Junye Road,  
Guangzhou GETDD East  
510530, China

Tel: +86 (0)20 2839 9600

Fax: +86 (0)20 2820 8706

<http://www.honeywell.com>

X-MAP4P\_EN1.0

July 2019

© 2019 Honeywell International Inc.

**Honeywell**