



## Architects and Engineering Specification

### System Sensor L-Series Strobe

The strobe shall be a System Sensor L-Series Model \_\_\_\_\_ listed to UL 1638 and shall be approved for fire protective service. The strobe shall be wired as a primary signaling notification appliance and comply with the Americans with Disabilities Act requirements for visible signaling appliances, flashing at 1 Hz over the strobe's entire operating voltage range. The strobe shall have field-selectable candela settings including 15, 30, 75, 95, 110, 135, 185 for wall mounted units and 15, 30, 75, 95, 115, 150, 177 for ceiling mounted units. The strobe light shall consist of a xenon flash tube and associated lens/reflector system. Indoor L-Series products shall operate between 32 and 120 degrees Fahrenheit from a regulated DC or full-wave rectified unfiltered power supply.

The strobe shall mount to a standard 4 × 4 × 1½ -inch back box, 4-inch octagon back box, double gang back box, and single-gang 2 × 4 × 17/8-inch back box. A universal mounting plate shall be used for mounting ceiling and standard wall products. A separate mounting plate shall be used for mounting compact wall products. The notification appliance circuit wiring shall terminate at the mounting plate.

The L-Series strobe and the Sync•Circuit™ Module MDL3 accessory, if used, shall be powered from a non-coded notification appliance circuit output and shall operate on a nominal 12 or 24 volts. When used with the Sync•Circuit Module MDL3, 12-volt-rated notification appliance circuit outputs shall operate between 8.5 and 17.5 volts; 24-volt-rated notification appliance circuit outputs shall operate between 16.5 and 33 volts. If the notification appliances are not UL 9th edition listed with the corresponding panel or power supply being used, then refer to the compatibility listing of the panel to determine maximum devices on a circuit.

The strobe shall be plug-in and shall have the ability to check wiring continuity via a shorting spring on the universal mounting plate. The shorting spring shall also provide tamper resistance via an open circuit if the device is removed. All notification appliances shall be backward compatible.