

ROM-300 / ROM-400

SCS-8/8L Software Compatibility Product Installation Document

PN LS10151-250GE-E:B 9/22/15 15-0518

ROM-300 / ROM-400 is included with each SCS series product as a separately packaged item, or may be ordered separately for existing systems that support V3.00 or V4.00 operation (see table below). Additional information on features supported by ROM-300 / ROM-400 when used with compatible panels and firmware are available in the current Smoke Control Manual.

The table below describes the SCS-8/8L software version compatibility with the various panels.

Panels	V2.84	V2.84Bxx	V3.00 or V4.00
Legacy	X		
NFS-320/NFS2-640, IFC-320/IFC2-640, XLS120/XLS-140-2 (HVAC only)	X		
NFS2-3030/NCA-2, IFC-3030/JNCA-2, XLS3000/XLS-NCA2 (< V21)	X	X	
NFS2-3030/NCA-2, IFC-3030/JNCA-2, XLS3000/XLS-NCA2 (V21 or higher)	X	X	X
• Enhanced Trouble Reporting			X
• Logic Zone Operators (AUTO, NORM, SCSDIS)			X
• Programmable Trouble Delay Timer			X
• FSCS Pairing			X
• MSCS (Multiple Smoke Control Stations)			X

Table 1

If your application requires the feature enhancements (Refer to SCS Series Operation and Installation Manual 15712:J) included in SCS-8/8L (V4.00), the NFS2-3030/NCA-2, IFC-3030/JNCA-2, XLS3000/XLS-NCA2 must be running software V21 (or higher). V3.00 or V4.00 must be installed in the SCS-8/8L, replacing the original ROM chip that comes with the product. Follow the ROM chip replacement instructions in document 15744.

NOTE: Firmware version 2.84 includes special versions ROM-284B60 and ROM-284B90, which provide ROM-284B60 sixty-second verification timer or ROM-284B90 ninety-second verification timer.
