Gamewell FCI FIRE CONTROL INSTRUMENTS by Honeywell

Technical Bulletin

Date: August 5, 2013 No. T13.3

To: All Gamewell-FCI Distributors

Updated Software Compatibility Charts

Upgrade choices concerning E3 firmware, FocalPoint® and CAMWorks!

With the listing of ANSI/UL 2572 (marketing update M13.10), our E3 Series product line has added new firmware and software. We understand keeping track of CAMWorks and E3 firmware versions can be difficult at best. Gamewell-FCI developed a series of compatibility charts to visually assist you in proper selection of E3 firmware.

E3 Firmware Compatibility Chart

Firmware Compatibility Document		ILI-MB / S							ILI95-MB / S							NGA						ANX			7100		
		v 1.04.001	v1.05.002	v 1.07.011	v2.04.088	v2.06.003	v2.07.061	v3.00.116	v1.09.001	v2.00.002	v2.02.011	v2.04.088	v2.06.003	v2.07.061	v3.00.116	v2.00.691	v2.10.014	v2.20.024	v2.30.003	v2.31.001	v3.00.240	v1.00.049	v1.10.005	v1.20.070	v6.04.160	v7.01.001	v7.00.156
ILI-MB / S	v 1.04.001								X							X									X*	X*	X*
	v1.05.002									X							X					X				X*	X*	X*
	v 1.07.011										X						X					X				X*	X*	X*
	v2.04.088											X						X				X				X*	X*	X*
	v2.06.003												X						X				X			X*	X*	X*
	v2.07.061													X						X			X			X*	X*	X*
	v3.00.116														X						X			X		X*	X*	X*
ILI95-MB / S	v1.09.001	X														X									N/A	N/A	N/A
	v2.00.002		X														X					X			N/A	N/A	N/A
	v2.02.011			X													X					X			N/A	N/A	N/A
	v2.04.086				X													X				X			N/A	N/A	N/A
	v2.06.003					X													X				X		N/A	N/A	N/A
	v2.07.061						X													X			X		N/A	N/A	N/A
	v3.00.116							X													X			X				
NGA	v2.00.691	X							X																X	X	X
	v2.10.014		X	X						X	X											X			X	X	X
	v2.20.024				X							X										X			X	X	X
	v2.30.003					X							X										X		X	X	X
	v2.31.001						X							X									X		X	X	X
	v3.00.240							X							X									X	X	X	X
ANX	v1.00.049		X	X	X					X	X	X					X	X							N/A	N/A	N/A
	v1.10.005					X	X						X	X					X	X					N/A	N/A	N/A
	v1.20.070							X							X						X				N/A	N/A	N/A
7100	v6.04.160	X*	X*	X*	X*	X*	X*	X*	N/A	N/A	N/A	N/A	N/A	N/A	N/A	X	X	X	X	X	X	N/A	N/A	N/A			
	v7.01.001	X*	X*	X*	X*	X*	X*	X*	N/A	N/A	N/A	N/A	N/A	N/A	N/A	X	X	X	X	X	X	N/A	N/A	N/A			
	v7.00.156	X*	X*	X*	X*	X*	X*	X*	N/A	N/A	N/A	N/A	N/A	N/A	N/A	X	X	X	X	X	X	N/A	N/A	N/A			

X* Downgrades the ILI to 7100 format

CAMWorks and Focal Point Compatibility Chart

	CAMWorks & Focal Point Compatibility Chart	CAMWorks 1.23.03	7100 StandAlone 7.03.02	7100 NetSolo 7.03.02	CAMWorks 2.10.33	CAMWorks 2.11.09	CAMWorks 2.20.25	CAMWorks 2.30.10	CAMWorks 2.40.012	FocalPoint 3.12.126	FocalPoint 3.14.132	FocalPoint 3.16.136	FocalPoint 3.18.162	FocalPoint 3.20.XXX
ILI-MB/S	v 1.04.001	X			X	X	X	X	X	X				
	v1.05.002	X			X	X	X	X	X		X	X		
	v 1.07.011				X	X	X	X	X		X	X		
	v2.04.088						X	X	X			x		
	v2.06.003							X	X			X**	X***	
	v2.07.061							X	X			X**	X***	
	v3.00.116								X				X***	
ILI95-MB/S	v1.09.001	X								X				
	v2.00.002				X	X	X	X	X		X	X		
	v2.02.011				X	X	X	X	X		X	X		
	v2.04.086						X	X	X			X		
	v2.06.003							X	X			X**	X***	
	v2.07.061							X	X			X**	X***	
	v3.00.116								X				X***	
NGA	v2.00.691	X		X	X	X	X	X		X	X			
	v2.10.014	X		X	X	X	X	X	X		X	X		
	v2.20.024						X	X	X			X		
	v2.30.003							X	X			X		
	v2.31.001							X	X			X	X***	
	v3.00.240								X				X***	
ANX	v1.00.049				X	X	X		X		X	X	X***	
	v1.10.005							X	X			X	X	
	v1.20.070								X				X	
7100	v6.04.160	X	X	X	X	X	X	X	X	X*	X**	X**	X***	
	v7.01.001	X	X	X	X	X	X	X	X	X*	X**	X**	X***	
	v7.00.156	X	X	X	X	X	X	X	X	X*	X**	X**	X***	

X*	Supports stand-alone (SA) or Network with an ILI-MB
X**	Does not support photo CO
X**	Supports stand-alone (SA) Only
X***	Supports Window 7-64bit Only

7100 Compatibility Chart

7100 Compatibility Document		FCP v2.0	FCP v3.3	FCP v4.0	FCP v5.5	FCP v6.1	FCP v6.5.0	FCP v6.5.2	FCP v7.00.16	FCP v7.01.11	FCP v7.03.02
7100 Firmware	v2	**X									
	v3		**X								
	v4			**X							
	v5				X						
	v6.1-001					X	X	X	X	X	X
	v6.2-003					X	X	X	X	X	X
	v6.3-001					X	X	X	X	X	X
	v6.3-011					X	X	X	X	X	X
	v6.4-008					X	X	X	X	X	X
	v6.4-133					X	X	X	X	X	X
	v6.4-156					*X	*X	*X	*X	*X	*X
	V6.4-160					*X	*X	*X	*X	*X	*X
	v7.0-045					*X	*X	*X	*X	*X	*X
	v7.0-133					*X	*X	*X	*X	*X	*X
	V7.0-156					*X	*X	*X	*X	*X	*X
	v7.0-160					*X	*X	*X	*X	*X	*X
	v7.1.001								*X	*X	*X

*X	Use PCB Rev C or Higher UL864
**X	Can be flashed to version 5 along with upgrading FCP
Notes	
1	8th Edition boards support firmware chips v 2.0 through v 6.4-160 but not v7 firmware
2	9th Edition boards support firmware chips v 7 only
3	V2 -V5 flashable up to V5, In order to ugrade to V6 need to replace U3

Gateway & Workstation Compatibility Chart

Focal Point Workstation & Gateway Compatibility Chart		WorkStation 3.0.145	WorkStation 3.0.205	WorkStation 3.10.122	WorkStation 3.11.124	WorkStation 3.12.126	WorkStation 3.14.130	WorkStation 3.16.138	WorkStation 3.18.176
BNA	3.2.5	X	X						
	3.3.2	X	X						
	3.3.6	X	X						
	3.10.122			X					
	3.11.124				X				
	3.12.126					X			
	3.14.130						X		
	3.16.132							X	
	3.18.176								X
Gate-3	3.11.124				X				
	3.12.126					X			
	3.14.130						X		
	3.16.138							X	
	3.18.176								X
	3.20.???								X
Gate-3-R	3.12.154					X			
	3.16.228							X	
	3.18.176								X
	3.20.???								X

Focal Point Gateway Compatibility Chart

Focal Point Gateway Compatibility Chart		Windows XP	Windows 7 64 Bit
FPT-Gate	3.2.5	X	
	3.3.2	X	
	3.3.6	X	
	3.10.122	X	
	3.11.124	X	
	3.12.126	X	
	3.14.130	X	
	3.16.132	X	X
	3.18.176		X
FPT-Gate-3	3.11.124	X	
	3.12.126	X	
	3.14.130	X	
	3.16.138	X	X
	3.18.176		X
	3.20.???		X
FPT-Gate-3-R	3.12.154	X	
	3.16.228	X	
	3.18.176		X
	3.20.???		X

Focal Point Workstation Compatibility Chart

Focal Point Workstation Compatibility Chart		Windows XP	Windows 7 64 Bit
WorkStation	3.0.145	X	
	3.0.205	X	
	3.10.122	X	
	3.11.124	X	
	3.12.126	X	
	3.14.130	X	
	3.16.138	X	X
	3.18.176		X

Focal Point Workstation Java Compatibility Chart

Focal Point Workstation Java Compatibility Chart		Java V 6	Java V 7
WorkStation	3.0.145		
	3.0.205		
	3.10.122		
	3.11.124		
	3.12.126		
	3.14.130	X	
	3.16.138	X	
	3.18.176		X

If you have any questions, please contact Gamewell-FCI Technical Support at 1-800-274-4324.

Sean Murphy
Supervisor
Engineering Technical Support
Gamewell-FCI by Honeywell

Bob Gomersall
Customer Product Manager
Gamewell-FCI by Honeywell