Gamewell FCI FIRE CONTROL INSTRUMENTS by Honeywell

Technical Bulletin

Date: January 2016 No. T16.1

To: All Gamewell-FCI Distributors

Updated Software Compatibility Charts – Fire Suppression Agent Releasing!

Making the correct choices concerning E3/S3 firmware, FocalPoint® and CAMWorks!

Fire suppression agent releasing applications are now available with the E3 Series! Our technical department has developed a series of compatibility charts to visually assist in making the correct selection of firmware, as well as the compatible version of CAMWorks required for system upgrades. Please be sure to review the following compatibility chart ensure correct firmware selection.

Firmware Compatibility Chart

Chart 1: ILI-MB/S, ILI95-MB/S, ILI-MB/S-PCA and NGA

Firmware Compatibility Document	ILI-MB / S									ILI95-MB / S								ILI-MB/S-PCA			NGA						
	v 1.04.001	v1.05.002	v 1.07.011	v2.04.088	v2.06.003	v2.07.061	v3.00.116	v3.01.051	v3.02.285	v1.09.001	v2.00.002	v2.02.011	v2.04.088	v2.06.003	v2.07.061	v3.00.116	v3.01.051	v3.02.285	v4.00.114	4.02.003	v4.03.190	v2.00.691	v2.10.014	v2.20.024	v2.30.003	v2.31.001	v3.00.240	v3.10.142	v3.30.032
ILI-MB / S v 1.04.001										X												X							
ILI-MB / S v1.05.002											X												X						
ILI-MB / S v 1.07.011												X											X						
ILI-MB / S v2.04.088													X											X					
ILI-MB / S v2.06.003														X											X				
ILI-MB / S v2.07.061															X											X			
ILI-MB / S v3.00.116																X											X		
ILI-MB / S v3.01.051																	X										X		
ILI-MB / S v3.02.285																		X	X***	X***	X****							X	
ILI95-MB / S v1.09.001	X																					X							
ILI95-MB / S v2.00.002		X																					X						
ILI95-MB / S v2.02.011			X																				X						
ILI95-MB / S v2.04.086				X																				X					
ILI95-MB / S v2.06.003					X																				X				
ILI95-MB / S v2.07.061						X																				X			
ILI95-MB / S v3.00.116							X																				X		
ILI95-MB / S v3.01.051								X																			X		
ILI95-MB / S v3.02.285									X										X***	X***	X****							X	
ILI-MB/S-PCA v4.00.114									X									X***										X***	
ILI-MB/S-PCA v4.02.003																		X***										X***	
ILI-MB/S-PCA v4.03.190																		X***											X****
NGA v2.00.691	X									X																			
NGA v2.10.014		X	X								X	X																	
NGA v2.20.024				X									X																
NGA v2.30.003					X									X															
NGA v2.31.001						X									X														
NGA v3.00.240							X	X								X	X												
NGA v3.10.142									X									X***	X***	X***									
NGA v3.30.032																		X***			X****								

X*	Downgrades the ILI to 7100 format
X**	Only upgradeable when RPT is connected to the S3 panel
X***	Only upgradeable when using ILI-MB/S-PCA version of the ILI
X****	Compatible with Fire Suppression Agent Releasing Applications

Firmware Compatibility Chart (continued)

Chart 2: ANX, 7100, S3, LCD-SLP, and RPT-E3

	Firmware Compatibility Document	ANX					7100					S3					LCD-SLP					RPT-E3	
		v1.00.049	v1.10.005	v1.20.070	v1.30.079		v6.04.160	v7.00.156	v7.01.001	v7.02.024		v1.00.026	v1.01.019	v1.11.009	v1.13.001		v1.00.112	v1.01.123	v1.02.001	v2.00.070	2.10.028	v1.00.057	v1.01.001
ILI-MB / S	v 1.04.001						X*	X*	X*	X*												X	X**
	v1.05.002	X					X*	X*	X*	X*												X	X**
	v 1.07.011	X					X*	X*	X*	X*												X	X**
	v2.04.088	X					X*	X*	X*	X*												X	X**
	v2.06.003		X				X*	X*	X*	X*												X	X**
	v2.07.061		X				X*	X*	X*	X*												X	X**
	v3.00.116			X			X*	X*	X*	X*												X	X**
	v3.01.051			X					X*	X*		X	X				X	X				X	X**
	v3.02.285				X				X*	X*				X	X				X	X		X	X**
ILI95-MB / S	v1.09.001						N/A	N/A	N/A	N/A												X	X**
	v2.00.002	X					N/A	N/A	N/A	N/A												X	X**
	v2.02.011	X					N/A	N/A	N/A	N/A												X	X**
	v2.04.086	X					N/A	N/A	N/A	N/A												X	X**
	v2.06.003		X				N/A	N/A	N/A	N/A												X	X**
	v2.07.061		X				N/A	N/A	N/A	N/A												X	X**
	v3.00.116			X			N/A	N/A	N/A	N/A												X	X**
	v3.01.051			X			N/A	N/A	N/A	N/A		X	X				X	X				X	X**
	v3.02.285				X		N/A	N/A	N/A	N/A				X	X				X	X		X	X**
ILI-MB/S-PCA	v4.00.114				X***										X***					X***			X**
	v4.02.003				X***										X***					X***			X**
	v4.03.190				X****										X***						x****		X**
NGA	v2.00.691						X	X	X	X												X	X**
	v2.10.014	X					X	X	X	X												X	X**
	v2.20.024	X					X	X	X	X												X	X**
	v2.30.003		X				X	X	X	X												X	X**
	v2.31.001		X				X	X	X	X												X	X**
	v3.00.240			X			X	X	X	X		X	X				X	X				X	X**
	v3.10.142				X				X	X				X	X				x	X		X	X**
	v3.30.032				X****																X****		

X*	Downgrades the ILI to 7100 format
X**	Only upgradeable when RPT is connected to the S3 panel
X***	Only upgradeable when using ILI-MB/S-PCA version of the ILI
X****	Compatible with Fire Suppression Agent Releasing Applications

Firmware Compatibility Chart (continued)

Chart 3: ILI-MB/S, ILI95-MB/S, ILI-MB/S-PCA and NGA

	Firmware Compatibility Document	ILI-MB / S									ILI95-MB / S								ILI-MB/S-PCA			NGA								
		v 1.04.001	v1.05.002	v 1.07.011	v2.04.088	v2.06.003	v2.07.061	v3.00.116	v3.01.051	v3.02.285	v1.09.001	v2.00.002	v2.02.011	v2.04.088	v2.06.003	v2.07.061	v3.00.116	v3.01.051	v3.02.285	v4.00.114	4.02.003	v4.03.190	v2.00.691	v2.10.014	v2.20.024	v2.30.003	v2.31.001	v3.00.240	v3.10.142	v3.30.032
ANX	v1.00.049		X	X	X							X	X	X										X	X					
	v1.10.005					X	X								X	X										X	X			
	v1.20.070							X	X								X	X										X		
	v1.30.079									X									X	X***	X***	X****							X	X****
7100	v6.04.160	X*	X*	X*	X*	X*	X*	X*			N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A				X	X	X	X	X	X		
	v7.00.156	X*	X*	X*	X*	X*	X*	X*			N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A				X	X	X	X	X	X		
	v7.01.001	X*	X*	X*	X*	X*	X*	X*	X*		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A				X	X	X	X	X	X		
	v7.02.024								X*	X*								N/A	N/A									X	X	
S3	v1.00.026								X									X										X		
	v1.01.019								X									X										X		
	v1.11.009									X									X										X	
	v1.13.001									X									X	X***	X***	X***							X	
LCD-SLP	v1.00.112																											X		
	v1.01.123																											X		
	v1.02.001									X									X	X***	X***								X	
	v2.00.070									X									X	X***	X***								X	
	v2.10.028																					X****								X****
RPT-E3	v1.00.057									X									X				X	X	X	X	X	X	X	
	v1.01.001									X**									X**	X***	X***	X****	X	X	X	X	X	X	X	

X*	Downgrades the ILI to 7100 format
X**	Only upgradeable when RPT is connected to the S3 panel
X***	Only upgradeable when using ILI-MB/S-PCA version of the ILI
X****	Compatible with Fire Suppression Agent Releasing Applications

Firmware Compatibility Chart (continued)

Chart 4: ANX, 7100, S3, LCD-SLP, and RPT-E3

	Firmware Compatibility Document	ANX					7100					S3					LCD-SLP					RPT-E3		
		v1.00.049	v1.10.005	v1.20.070	v1.30.079		v6.04.160	v7.00.156	v7.01.001	v7.02.024		v1.00.026	v1.01.019	v1.11.009	v1.13.001		v1.00.112	v1.01.123	v1.02.001	v2.00.070	2.10.028	v1.00.057	v1.01.001	
ANX	v1.00.049						N/A	N/A	N/A	N/A												X	X**	
	v1.10.005						N/A	N/A	N/A	N/A												X	X**	
	v1.20.070						N/A	N/A	N/A	N/A		X	X				X	X				X	X**	
	v1.30.079									N/A				X	X				X	X	x****	X	X**	
7100	v6.04.160	N/A	N/A	N/A																				
	v7.00.156	N/A	N/A	N/A																				
	v7.01.001	N/A	N/A	N/A								X	X	X	X		X	X	X					
	v7.02.024			N/A	N/A							X	X	X	X		X	X	X					
S3	v1.00.026			X					X	X							X	X				X	X**	
	v1.01.019			X					X	X							X	X				X	X**	
	v1.11.009				X					X									X			X	X**	
	v1.13.001				X					X										X	X		X**	
LCD-SLP	v1.00.112			X					X	X		X	X											
	v1.01.123			X					X	X		X	X											
	v1.02.001				X				X	X				X										
	v2.00.070				X										X									
	v2.10.028				X****										X									
RPT-E3	v1.00.057	X	X	X	X							X	X	X										
	v1.01.001	X**	X**	X**	X**							X**	X**	X**	X**									

X*	Downgrades the ILI to 7100 format
X**	Only upgradeable when RPT is connected to the S3 panel
X***	Only upgradeable when using ILI-MB/S-PCA version of the ILI
X****	Compatible with Fire Suppression Agent Releasing Applications

CAMWorks Compatibility Chart

Chart 1: ILI-MB/S, ILI95-MB/S, ILI-MB/S-PCA, NGA

CAMWorks & Focal Point Compatibility Chart		CAMWorks 1.23.03	7100 StandALone 7.03.02	7100 NetSolo 7.03.02	CAMWorks 2.10.33	CAMWorks 2.11.09	CAMWorks 2.20.25	CAMWorks 2.30.10	CAMWorks 2.40.012	CAMWorks 3.00.016	CAMWorks 3.10.007	CAMWorks 3.20.028	CAMWorks 3.21.002	CAMWorks 3.30.017	CAMWorks 3.31.000	CAMWorks 3.32.002	CAMWorks 3.40.015	CAMWorks 3.41.001
ILI-MB/S	v 1.04.001	X			X	X	X	X	X	X		X	X	X	X	X	X	X
	v1.05.002	X			X	X	X	X	X	X		X	X	X	X	X	X	X
	v 1.07.011				X	X	X	X	X	X		X	X	X	X	X	X	X
	v2.04.088						X	X	X	X		X	X	X	X	X	X	X
	v2.06.003							X	X	X		X	X	X	X	X	X	X
	v2.07.061							X	X	X		X	X	X	X	X	X	X
	v3.00.116								X	X	X	X	X	X	X	X	X	X
	v3.01.051									X	X	X	X	X	X	X	X	X
	v3.02.285											X	X	X	X	X	X	X
	v3.03.064													X	X	X	X	X
ILI95-MB/S	v1.09.001	X																
	v2.00.002				X	X	X	X	X	X		X	X	X	X	X	X	X
	v2.02.011				X	X	X	X	X	X		X	X	X	X	X	X	X
	v2.04.086						X	X	X	X		X	X	X	X	X	X	X
	v2.06.003							X	X	X		X	X	X	X	X	X	X
	v2.07.061							X	X	X		X	X	X	X	X	X	X
	v3.00.116								X	X	X	X	X	X	X	X	X	X
	v3.01.051									X	X	X	X	X	X	X	X	X
	v3.02.285											X	X	X	X	X	X	X
ILI-MB/S-PCA	v4.00.114													X	X	X	X	X
	v4.02.003													X	X	X	X	X
	v4.03.190																X	X
NGA	v2.00.691	X		X	X	X	X	X										
	v2.10.014	X		X	X	X	X	X	X	X	X	X	X	X	X	X	X	X
	v2.20.024						X	X	X	X	X	X	X	X	X	X	X	X
	v2.30.003							X	X	X	X	X	X	X	X	X	X	X
	v2.31.001							X	X	X	X	X	X	X	X	X	X	X
	v3.00.240								X	X	X	X	X	X	X	X	X	X
	v3.10.142											X	X	X	X	X	X	X
	v3.30.032																	X

X*	Supports Stand Alone (SA) or Network with an ILI-MB
X**	Does not support photo CO
X**	Supports Stand Alone (SA) Only
X***	Supports Window 7-64bit Only

CAMWorks Compatibility Chart (continued)

Chart 2: ANX, 7100, S3, LCD-SLP, RPT-E3

	CAMWorks & Focal Point Compatibility Chart	CAMWorks 1.23.03	7100 StandALone 7.03.02	7100 NetSolo 7.03.02	CAMWorks 2.10.33	CAMWorks 2.11.09	CAMWorks 2.20.25	CAMWorks 2.30.10	CAMWorks 2.40.012	CAMWorks 3.00.016	CAMWorks 3.10.007	CAMWorks 3.20.028	CAMWorks 3.21.002	CAMWorks 3.30.017	CAMWorks 3.31.000	CAMWorks 3.32.002	CAMWorks 3.40.015	CAMWorks 3.41.001
ANX	v1.00.049				X	X	X		X	X	X	X	X	X	X	X	X	X
	v1.10.005							X	X	X	X	X	X	X	X	X	X	X
	v1.20.070								X	X	X	X	X	X	X	X	X	X
	v1.30.079											X	X	X	X	X	X	X
7100	v6.04.160	X	X	X	X	X	X	X	X	X	X		X	X	X	X	X	X
	v7.00.156	X	X	X	X	X	X	X	X	X	X		X	X	X	X	X	X
	v7.01.001	X	X	X	X	X	X	X	X	X	X		X	X	X	X	X	X
	v7.02.024			X				X	X	X	X	X	X	X	X	X	X	X
S3	v1.00.026									X	X		X	X	X	X	X	X
	v1.01.019									X	X	X	X	X	X	X	X	X
	v1.11.009												X	X	X	X	X	X
	v1.13.001													X	X	X	X	X
LCD-SLP	v1.00.112									X	X							
	v1.01.123									X	X	X	X					
	v1.02.001											X	X					
	v2.00.070													X	X	X	X	X
	v2.10.027																X	X
RPT-E3	v1.00.057									X	X	X	X	X	X	X	X	X
	v1.01.001									X	X	X	X	X	X	X	X	X

X*	Supports Stand Alone (SA) or Network with an ILI-MB
X**	Does not support photo CO
X**	Supports Stand Alone (SA) Only
X***	Supports Window 7-64bit Only

FocalPoint® Compatibility Chart

Chart 1: ILI-MB/S, ILI95-MB/S, ILI-MB/S-PCA, NGA

CAMWorks & Focal Point Compatibility Chart		FocalPoint 3.12.126	FocalPoint 3.14.132	FocalPoint 3.16.136	FocalPoint 3.18.176	FocalPoint 3.22.154	FocalPoint 3.24.142
ILI-MB/S	v 1.04.001	X					
	v1.05.002		X	X			
	v 1.07.011		X	X			
	v2.04.088			x			
	v2.06.003			X	X***	X***	X***
	v2.07.061			X	X***	X***	X***
	v3.00.116				X***	X***	X***
	v3.01.051				X***	X***	X***
	v3.02.285						X***
	v3.03.064						
ILI95-MB/S	v1.09.001	X					
	v2.00.002		X	X			
	v2.02.011		X	X			
	v2.04.086			X			
	v2.06.003			X	X***	X***	X***
	v2.07.061			X	X***	X***	X***
	v3.00.116				X***	X***	X***
	v3.01.051				X***	X***	X***
	v3.02.285					X***	X***
ILI-MB/S-PCA	v4.00.114						X***
	v4.02.003						X***
	v4.03.190						
NGA	v2.00.691	X	X				
	v2.10.014		X	X			
	v2.20.024			X			
	v2.30.003			X			
	v2.31.001			X	X***	X***	X***
	v3.00.240				X***	X***	X***
	v3.10.142					X***	X***
	v3.30.032						

X*	Supports Stand Alone (SA) or Network with an ILI-MB
X**	Does not support photo CO
X**	Supports Stand Alone (SA) Only
X***	Supports Window 7-64bit Only

FocalPoint® Compatibility Chart (continued)

Chart 2: ANX, 7100, S3, LCD-SLP, RPT-E3

CAMWorks & Focal Point Compatibility Chart		FocalPoint 3.12.126	FocalPoint 3.14.132	FocalPoint 3.16.136	FocalPoint 3.18.176	FocalPoint 3.22.154	FocalPoint 3.24.142
ANX	v1.00.049		X	X	X***	X***	X***
	v1.10.005			X	X***	X***	X***
	v1.20.070				X***	X***	X***
	v1.30.079					X***	X***
7100	v6.04.160	X*	X**	X**	X***	X***	X***
	v7.00.156	X*	X**	X**	X***	X***	X***
	v7.01.001	X*	X**	X**	X***	X***	X***
	v7.02.024					X***	X***
S3	v1.00.026					X***	X***
	v1.01.019					X***	X***
	v1.11.009					X***	X***
	v1.13.001						
LCD-SLP	v1.00.112						
	v1.01.123						
	v1.02.001						
	v2.00.070						
	v2.10.027						
RPT-E3	v1.00.057						
	v1.01.001						

X*	Supports Stand Alone (SA) or Network with an ILI-MB
X**	Does not support photo CO
X**	Supports Stand Alone (SA) Only
X***	Supports Window 7-64bit Only

7100 Compatibility Chart

7100 Compatibility		FCP v2.0	FCP v3.3	FCP v4.0	FCP v5.5	FCP v6.1	FCP v6.5.0	FCP v6.5.2	FCP v7.00.16	FCP v7.01.11	FCP v7.03.02
7100 Firmware	v2	**X									
	v3		**X								
	v4			**X							
	v5				X						
	v6.1-001					X	X	X	X	X	X
	v6.2-003					X	X	X	X	X	X
	v6.3-001					X	X	X	X	X	X
	v6.3-011					X	X	X	X	X	X
	v6.4-008					X	X	X	X	X	X
	v6.4-133					X	X	X	X	X	X
	v6.4-156					*X	*X	*X	*X	*X	*X
	V6.4-160					*X	*X	*X	*X	*X	*X
	v7.0-045					*X	*X	*X	*X	*X	*X
	v7.0-133					*X	*X	*X	*X	*X	*X
	V7.0-156					*X	*X	*X	*X	*X	*X
	v7.0-160					*X	*X	*X	*X	*X	*X
	v7.1.001								*X	*X	*X
	v7.2.024										*X

*X	Use PCB Rev C or Higher UL864
**X	Can be flashed to version 5 along with upgrading FCP
	Notes
1	8th Edition boards support firmware chips v 2.0 through v 6.4-160 but not v7 firmware
2	9th Edition boards support firmware chips v 7 only
3	V2 -V5 flashable up to V5, In order to ugrade to V6 need to replace U3

Gateway & Workstation Compatibility Chart

Focal Point Workstation & Gateway Compatibility Chart		WorkStation 3.0.145	WorkStation 3.0.205	WorkStation 3.10.122	WorkStation 3.11.124	WorkStation 3.12.126	WorkStation 3.14.130	WorkStation 3.16.138	WorkStation 3.18.176	WorkStation 3.22.154	WorkStation 3.24.142
BNA	v3.2.5	X	X								
	v3.3.2	X	X								
	v3.3.6	X	X								
	v3.10.122			X							
	v3.11.124				X						
	v3.12.126					X					
	v3.14.130						X				
	v3.16.132							X			
	v3.18.176								X		
	v3.20.108								X		
Gate-3	v3.11.124				X						
	v3.12.126					X					
	v3.14.130						X				
	v3.16.138							X			
	v3.18.176								X		
	v3.20.108								X		
	v3.22.154									X	
	v3.24.142										X
Gate-3-R	v3.12.154					X					
	v3.16.228							X			
	v3.18.176								X		
	v3.20.108								X		
	v3.22.154									X	
	v3.24.142										X

Note:
1. The BNA gateway is no longer support after v3.20.108
2. V3.22.154 gateway no longer supports Java Script, it uses HTML 5

FocalPoint® Gateway & Workstation Compatibility Chart

Chart 1: FocalPoint® Gateway Compatibility

Focal Point Gateway Compatibility Chart		Windows XP	Windows 7 64 Bit
FPT-Gate	v3.2.5	X	
	v3.3.2	X	
	v3.3.6	X	
	v3.10.122	X	
	v3.11.124	X	
	v3.12.126	X	
	v3.14.130	X	
	v3.16.132	X	X
	v3.18.176		x
	v3.20.108		X
FPT-Gate-3	v3.11.124	X	
	v3.12.126	X	
	v3.14.130	X	
	v3.16.138	X	X
	v3.18.176		X
	v3.20.108		X
	v2.22.154		X
	v3.24.142		X
FPT-Gate-3-R	v3.12.154	X	
	v3.16.228	X	X
	v3.18.176		X
	v3.20.108		X
	v3.22.154		X
	v3.24.142		X

Chart 2: FocalPoint® Workstation Compatibility

Focal Point Workstation Compatibility Chart		Windows XP	Windows 7 64 Bit
WorkStation	v3.0.145	X	
	v3.0.205	X	
	v3.10.122	X	
	v3.11.124	X	
	v3.12.126	X	
	v3.14.130	X	
	v3.16.138	X	X
	v3.18.176		X
	v3.22.154		X
	v3.24.142		X

Chart 3: FocalPoint® Workstation Java/HTML Compatibility

Focal Point Workstation Java/HTML Compatibility Chart		Java V 6	Java V 7	HTML5
WorkStation	v3.0.145			
	v3.0.205			
	v3.10.122			
	v3.11.124			
	v3.12.126			
	v3.14.130	X		
	v3.16.138	X		
	v3.18.176		X	
	v3.20.108		X	
	v3.22.154			X
	v3.24.142			X

Support

For additional questions or support on system compatibility, please contact Gamewell-FCI Technical Support at 1-800-274-4324

Sincerely,



Chuck Han
Product Marketing
Honeywell Security and Fire
Gamewell-FCI by Honeywell