



# Magnetic Sensor IC Selection Chart

## A Technical Note

Tables 1, 2, 3, and 4 provide an overview of Honeywell's Hall-effect and anisotropic magnetoresistive (AMR) sensor ICs.

**Table 1. Digital Position Sensor ICs**

Product Type	Package Style								Typical Operate (Gauss)	Typical Release (Gauss)	Maximum Operate (Gauss)	Reverse Polarity	Operating Temp. (°C)	Supply Voltage (Vdc)	Typical Current Supply (mA)
	SOT-23		TO-92-Style or U-Pack <sup>1</sup> Straight Standard Leads		TO-92-Style SMT		SOT-89B								
	Catalog Listing	Standard Label	Catalog Listing	Standard Label	Catalog Listing	Standard Label	Catalog Listing	Standard Label							
<b>Bipolar</b>															
Hall effect	SS30AT	S30A	SS40A	40A	—	—	SS50AT	SS50A	45	-45	170	yes	-40 to 125	4.5 to 24	6.8
	SS311PT	311P	SS411P	411P	—	—	—	—	60	-80	140	—	-40 to 150	2.7 to 7	5.5
	—	—	SS41	S41	—	—	SS51T	SS51	40	-40	250	yes	-40 to 150	4.5 to 24	5.8
	—	—	411A	11A	—	—	SS511AT	S511A	20	-20	70	—	-40 to 150	3.8 to 30	6.5
	—	—	SS413A	13A	—	—	SS513AT	S513A	50	-50	140	—	-40 to 150	3.8 to 30	6.5
<b>Latching</b>															
Hall effect	VF360NT <sup>2</sup>	360NT	VF460S <sup>2</sup>	460S	—	—	—	—	30	-30	55	yes	-40 to 150	3 to 24	4
	VF360ST <sup>2</sup>	360ST	—	—	—	—	—	—	—	—	—	—	—	—	—
	SS360NT	360NT	SS460S	460S	—	—	—	—	30	-30	55	yes	-40 to 150	3 to 24	4
	SS360ST	360ST	SS460P	460P	—	—	—	—	—	—	—	—	—	—	—
	SS360PT	360PT	—	—	—	—	—	—	—	—	—	—	—	—	—
	SS361RT	361RT	SS461R	461R	—	—	—	—	50	-50	120	yes	-40 to 150	3 to 24	4
SS361CT	361CT	SS461C	461C	—	—	—	—	50	-50	95	yes	-40 to 125	4 to 24	4	
—	—	SS461A	61A	—	—	—	S561A	50	-50	110	—	-40 to 150	3.8 to 30	6.5	
—	—	SS466A	66A	—	—	—	S566A	140	-140	200	—	-40 to 150	3.8 to 30	6.5	
<b>Unipolar</b>															
Hall effect	SS341RT	341RT	SS441R	441R	—	—	—	—	75	35	135	yes	-40 to 150	3 to 24	4
	SS343RT	343RT	SS443R	443R	—	—	—	—	135	85	205	yes	-40 to 150	3 to 24	4
	SS349RT	349RT	SS449R	449R	—	—	—	—	305	225	460	yes	-40 to 150	3 to 24	4
	SS345PT	345PT	SS445P	445P	—	—	—	—	180	105	280	—	-40 to 150	2.7 to 7	5.5
	—	—	SS441A	41A	SS541AT	S541A	—	—	85	58	135	—	-40 to 150	3.8 to 30	6.5
	—	—	SS443A	43A	SS543AT	S543A	—	—	145	115	215	—	-40 to 150	3.8 to 30	6.5
	—	—	SS449A	49A	SS549AT	S549A	—	—	350	275	435	—	-40 to 150	3.8 to 30	6.5
<b>Omnipolar</b>															
Hall effect	SS351AT	351AT	SS451A	451A	SS551AT	S551A	—	—	±85	±40	±135	yes	-40 to 150	3 to 24	4.5
AMR	—	—	2SS52M	2SSM	2SS52M-S	2SSM	2SS52MT	S552M	±15	±11	±25	—	-40 to 150	3.8 to 30	6.5
AMR Standard Power	SM351RT	SM351R	SM451R	451R	—	—	—	—	±7	±5	±11	—	-40 to 85	3 to 24	4
	SM353RT	SM353R	SM453R	453R	—	—	—	—	±14	±10	±20	—	-40 to 85	3 to 24	4
AMR Low Power	SM351LT	SM351L	—	—	—	—	—	—	±7	±5	±11	—	-40 to 85	1.65 to 5.5	0.36 μA
	SM353LT	SM353L	—	—	—	—	—	—	±14	±10	±20	—	-40 to 85	1.65 to 5.5	0.35 μA
Hall effect Low Power	SL353HT	L353H	—	—	—	—	—	—	±60	±45	±110	—	-40 to 85	2.2 to 5.5	330 μA
	SL353LT	L353L	—	—	—	—	—	—	±60	±45	±110	—	-40 to 85	2.2 to 5.5	1.8 μA

<sup>1</sup>U-pack package style applies to the 2SS52M Series only.

<sup>2</sup>Qualified to AEC-Q100 (Grade 0).

**Table 2. Linear Sensor ICs**

Package Style								Typical Sensitivity (mV/Gauss)	Typical Range (Gauss)	Operating Temp. (°C)	Supply Voltage (Vdc)	Typ. Current (mA)
SOT-23		TO-92-Style Straight Standard Leads		TO-92-Style SMT		SOT-89B						
Catalog Listing	Standard Label	Catalog Listing	Standard Label	Catalog Listing	Standard Label	Catalog Listing	Standard Label					
SS39ET	—	SS49ET	49E	—	—	SS59ET	SS59E	1.4	±1000	-40 to 100	2.7 to 6.5	6
—	—	SS494B	94B	SS494B-SP	94B	—	—	5.0	±420	-40 to 150	4.5 to 10.5	7
—	—	SS495A	95A	SS495A-SP	95A	—	—	3.125	±670	-40 to 150	4.5 to 10.5	7
—	—	SS495A1	95A	SS495A1-SP	95A	—	—	3.125	±670	-40 to 150	4.5 to 10.5	7
—	—	SS495A2	95A	SS495A2-SP	95A	—	—	3.125	±670	-40 to 150	4.5 to 10.5	7
—	—	SS495B	95B	SS495B-SP	95B	—	—	3.125	±670	-40 to 150	4.5 to 10.5	7
—	—	SS496A	96A	SS496A-SP	96A	—	—	2.50	±840	-40 to 150	4.5 to 10.5	7
—	—	SS496A1	96A	SS496A1-SP	96A	—	—	2.50	±840	-40 to 150	4.5 to 10.5	7
—	—	SS496B	96B	SS496B-SP	96B	—	—	2.50	±840	-40 to 150	4.5 to 10.5	7
—	—	—	—	VF495A1-SP <sup>1</sup>	495A	—	—	3.125	±670	-40 to 150	4.5 to 10.5	7

<sup>1</sup> Qualified to AEC-Q100 (Grade 0).

**Table 3. Angular AMR Position Sensor IC**

SOIC-8 Package Style		Typical Sensitivity (mV/deg.)	Typical Range (degree)	Operating Temp. (°C)	Supply Voltage (Vdc)	Current (mA)
Catalog Listing	Standard Label					
APS00B	—	2.1	±90	-40 to 150	1 to 12	7 max.

**Table 4. Speed and Direction, Speed Sensor ICs**

Product Type	Catalog Listing	Standard Label	Function	Target	Package Style	Output	Typical Sensitivity (Gauss)	Operating Temp. (°C)	Supply Voltage (Vdc)	Current (mA)		
AMR	VM721V1 <sup>1,2</sup>	VM721V1	speed sensing	ring magnet encoder	2-pin SIP, wide leads	2-pin current	±30	-40 to 150	-40°C to 110°C: 4.0 V to 24 V 150°C: 4.0 V to 9 V	high: 14 typ. low: 6.95 typ.		
	VM721D1 <sup>1,2</sup>	VM721D1 VM721D1	speed and direction sensing		2-pin SIP, wide leads	2-pin pulse width modulated (PWM)						
	VM821Q1	VM821Q1	speed and direction or position sensing		4-pin SIP	quadrature, dual open collector sinking					4.0 V to 24 V	20 max.
	VF401	VF401			VF401 2-pin, TO-92-style, straight standard leads	2-pin current					4.0 V to 16 V	high: 14 typ. low: 7 typ.
Hall-effect, back biased	VG481V1 <sup>1</sup>	VG481V1	speed sensing	ferrous gear tooth wheel	TO-92-style, straight standard leads	sinking	49.5	-40 to 150	4 V to 24 V	10 max.		
Hall effect, dual latching	VF526DT	V526	speed and direction sensing	ring magnet encoder	SOT-89B	dual open collector sinking	130	-40 to 125	3.4 V to 24 V	off: 12 max. on: 14 max.		
	SS526GT	S526G										

<sup>1</sup> Qualified to AEC-Q100 (Grade 0).

<sup>2</sup> ISO26262 ASIL B(D) compliant.

**For More Information**

Honeywell Sensing and Internet of Things services its customers through a worldwide network of sales offices and distributors. For application assistance, current specifications, pricing or the nearest Authorized Distributor, visit [sensing.honeywell.com](http://sensing.honeywell.com) or call:

Asia Pacific +65 6355-2828  
 Europe +44 (0) 1698 481481  
 USA/Canada +1-800-537-6945

**Warranty/Remedy**

Honeywell warrants goods of its manufacture as being free of defective materials and faulty workmanship during the applicable warranty period. Honeywell’s standard product warranty applies unless agreed to otherwise by Honeywell in writing; please refer to your order acknowledgement or consult your local sales office for specific warranty details. If warranted goods are returned to

Honeywell during the period of coverage, Honeywell will repair or replace, at its option, without charge those items that Honeywell, in its sole discretion, finds defective. **The foregoing is buyer’s sole remedy and is in lieu of all other warranties, expressed or implied, including those of merchantability and fitness for a particular purpose. In no event shall Honeywell be liable for consequential, special, or indirect damages.**

While Honeywell may provide application assistance personally, through our literature and the Honeywell web site, it is buyer’s sole responsibility to determine the suitability of the product in the application.

Specifications may change without notice. The information we supply is believed to be accurate and reliable as of this writing. However, Honeywell assumes no responsibility for its use.

**Honeywell Sensing and Internet of Things**

830 East Arapaho Road  
 Richardson, TX 75081  
[sensing.honeywell.com](http://sensing.honeywell.com)

