

SWITCHES FOR AUTOMATED PARKING GATES & BARRIERS

Application Note

BACKGROUND

Parking gates/barriers restrict entry, provide admittance, and reports an accurate count of vehicles entering and exiting the parking lot or structure. **If a gate does not operate as designed, downtime could result in loss of revenue due to service calls and inaccurate reporting of vehicles entering and exiting the parking lot.**

These gates can often be located in an open environment where they can be exposed to varying weather conditions or an open-air structure. Open environments can experience high and low temperature extremes (-40°C to 50°C), condensation within the device, and exposure to rain, dust, dirt, snow, oil, lubricants, and other elements which can affect the gate's performance.

SOLUTION

Honeywell offers basic and limit switch solutions to help ensure the gate's reliability and performance. For covered parking garages/structures in non-extreme weather conditions (where dust and moisture are not typical), Honeywell recommends the [MICRO SWITCH BZ Series basic switch](#). For harsh conditions and open-air parking facilities, Honeywell offers the [MICRO SWITCH E6/V6/E7/V7 Series](#) sealed limit switch. Switches are essential for gate reliability and functionality. These switches provide information about the position of the gate, assist the drive to operate correctly, and address open/closed requests from the system driven by motion sensors, cameras, scan engines, etc.

Both the BZ Series and the E6/V6/E7/V7 Series contain a similar basic switch (see Figure 2).

Both switches offer enhanced mechanical life. The BZ basic switch is **rated up to 20 million cycles**; whereas the E6/V6 is **rated up to 5 million cycles**.

Electrically, switches are capable of **switching logic level up to power-duty loads** for PLC and motor control applications. These Series can switch from **mA to up to 22 A**, and from low voltage **12 V to 240 V**. Therefore, this switch package can provide a wide variety of inputs to control systems.



Figure 1. MICRO SWITCH BZ Basic Switch or BZE6 Sealed Limit Switch Used in a Parking Gate Barrier Application

The switch is installed on a fixed pole where the arm rests and rotates (see Figure 1). When the arm opens and closes, the switch is actuated to signal a vehicle has either entered or exited. When the arm is down, the switch remains in the free state. Conversely, when the arm is raised, the switch is actuated.

The E6/V6 Series' standard temperature range is -32°C to 71°C [-25°F to 160°F] with an optional -40°C [-40°F] low temperature. The BZ Series basic switch has an operating temperature range of -55°C to 85°C [-67°F to 185°F].

Honeywell switches have elongated mounting holes that allow for **easier, more accurate mounting**, and also have sufficient space for wiring the contacts more easily and quickly. The BZ and the BZE6 Series features standard 25,4 mm mounting centers for global acceptance. The BZV7 switch has 41,3 mm mounting centers with 5,2 mm holes.

For dirty, dusty, harsh conditions, the **E6/V6 Series is sealed to IP66**, while the **E7/V7 Series is sealed to IP65** to prevent dust and liquid ingress.

MICRO SWITCH E6/V6 and E7/V7 Series switches feature an electrostatic epoxy coated metal housing for **durability in most indoor and outdoor environments**, and a wide variety of actuators to solve most application requirements.

These switches are suitable for global applications.

- BZ Series switches carry **UL, CSA, ENEC, CE and UKCA** approvals
- E6/V6 Series switches are **UL, CSA, CE and UKCA** certified for most SPDT catalog listings
- Most E7/V7 switches have approvals from **CSA, CE and UKCA**

BZ Basic Switch Features and Benefits

- Accepted world-wide standard "Large Basic" switch
- Low operating force and differential travel
- Long mechanical life up to 20,000,000 cycles at 95 % survival
- Elongated mounting hole for easier, more accurate mounting
- Current rating ranges from mA to 22 A
- Choice of actuation, termination, and operating characteristics

Figure 2. MICRO SWITCH BZ Basic Switch used in E6/V6/E7/V7 switches



E6/V6 and E7/V7 Limit Switch Features and Benefits

- Side or flange mount
- Wide variety of actuators
- Momentary or maintained contact
- Internal grounding screw
- Current range from mA to 22 A
- Temperature range -32°C to 71°C [-25°F to 160°F]
- Optional low temperature -40°C to 71°C
- UL Recognized, file #E12252
- CSA Certified, file #LR41372
- NEMA 1, 3, 4, and IP66 with rubber boot on plunger
- Pre-leaded or connector termination options



⚠ WARNING IMPROPER INSTALLATION

- Consult with local safety agencies and their requirements when designing a machine control link, interface and all control elements that affect safety.
- Strictly adhere to all installation instructions.

Failure to comply with these instructions could result in death or serious injury.

WARRANTY/REMEDY

Honeywell warrants goods of its manufacture as being free of defective materials and faulty workmanship during the applicable warranty period. Honeywell's standard product warranty applies unless agreed to otherwise by Honeywell in writing; please refer to your order acknowledgement or consult your local sales office for specific warranty details. If warranted goods are returned to Honeywell during the period of coverage, Honeywell will repair or replace, at its option, without charge those items that Honeywell, in its sole discretion, finds defective. **The foregoing is buyer's sole remedy and is in lieu of all other warranties, expressed or implied, including those of merchantability and fitness for a particular purpose. In no event shall Honeywell be liable for consequential, special, or indirect damages.**

While Honeywell may provide information or engineering support for its products through Honeywell personnel, literature and website, it is the buyer's sole responsibility to determine the suitability of the Honeywell product(s) for the buyer's requirements

Specifications may change without notice. The information we supply is believed to be accurate and reliable as of this writing. However, Honeywell assumes no responsibility for its use.

For more information

Honeywell Sensing Solutions services its customers through a worldwide network of sales offices and distributors. For application assistance, current specifications, pricing, or the nearest Authorized Distributor, visit automation.honeywell.com/hss or call:

USA/Canada	+302 613 4491
Latin America	+1 305 805 8188
Europe	+44 1344 238258
Japan	+81 (0) 3-6730-7152
Singapore	+65 6355 2828
Greater China	+86 4006396841

Honeywell Sensing Solutions

830 East Arapaho Road
Richardson, TX 75081
honeywell.com