



Architects and Engineering Specification

SpectrAlert Advance Low Frequency Sounder Strobe

The low frequency sounder strobe appliance shall be System Sensor model number _____. The low frequency sounder strobe shall be listed to UL 1971 and UL 464 and shall be approved for fire protective service. The low frequency sounder strobe shall be wired as a primary-signaling notification appliance and comply with the Americans with Disabilities Act requirements for visible signaling appliances, flashing at 1Hz over the strobe's entire operating voltage range. The strobe shall have field-selectable candela settings including 135, 150, 177, 185. The strobe light shall consist of a xenon flash tube and associated lens/reflector system. The low frequency sounder shall have an option to switch between a temporal three-pattern and a non-temporal (continuous) pattern. These options are set by a multiple position switch. The low frequency sounder on low frequency sounder/strobe models shall operate on a non-coded power supply. The low frequency strobe shall operate between 32°F and 120°F.

The low frequency sounder strobe shall mount to a standard 4 × 4 × 1½-inch back box, 4-inch octagon back box, double-gang back box or a single-gang or 2 × 4 × 17/8-inch back box. A universal mounting plate shall be used for mounting ceiling and wall products. The notification appliance circuit wiring shall terminate at the universal mounting plate.

The low frequency sounder strobe and the Sync•Circuit™ Module MDL3 accessory, if used, shall be powered from a non-coded notification appliance circuit output and shall operate on a nominal 24 volts (includes fire alarm panels with built in sync). When used with the Sync•Circuit Module MDL3, 24-volt rated notification appliance circuit outputs shall operate between 16.5 to 33 volts. If the notification appliances are not UL 9th edition listed with the corresponding panel or power supply being used, then refer to the compatibility listing of the panel to determine maximum devices on a circuit.

The low frequency sounder strobe shall be plug-in and shall have the ability to check wiring continuity via a shorting spring on the universal mounting plate. The shorting spring shall also provide tamper resistance via an open circuit if the device is removed.

All notification appliances shall be backward compatible.