



US DIGITAL DESIGNS
by Honeywell

RR-2

Room Remote 2

General

The Phoenix G2 Room Remote 2 is the all-in-one peripheral that simultaneously shows dispatched Units, incident information, turnout timer, and alert date/time. It features a 10.1 inch, full-color, high-resolution LCD multi-touch display for easily adjusting settings, such as units to be alerted, radio monitoring, speaker volume, and brightness. Automatic backlight control dims the display when an alert is not active.

The Phoenix G2 Room Remote 2 sends targeted dispatch messages to specific fire station units or rooms.

Popular uses for the Room Remote 2 include:

- Dorm Rooms – select alerts only for unit in dorm
- Offices – Monitor other station units' activity
- Training Rooms – volume control and quiet alerts



Specifications

- Power: Uses Phoenix G2 POE (Power over Ethernet)
- Current usage: 0.10/0.25 amps (avg/peak)
- 15 watt audio amplifier
- 1 Year Parts & Labor Warranty
- Service Contract Available
- Dimensions: 13.25" x 5.25" x 3.32" (WxHxL)

Product Line Information

- **RR-2.** Room Remote 2
- **RR2-AP.** Room Remote 2 Retrofit Adapter Plate
- **RR2-SMB.** Room Remote 2 Back Box
- **SPK-LED-FM.** LED S86 Speaker
- **SPK-LED-SM.** LED Box Speaker
- **SPK-STD-FM.** Flush Mount Speaker
- **SPK-STD-SM.** Surface Mount Speaker
- **ATX.** Station Alerting Controller (See data sheet USDD-62155)

US Digital Designs by Honeywell

1835 E. Sixth St. Suite #27
Tempe, AZ 85281 USA
877-551-USDD
stationalerting.com

This document is not intended to be used for installation purposes. We try to keep our product information up-to-date and accurate. We cannot cover all specific applications or anticipate all requirements. All specifications are subject to change without notice. Phoenix G2® is a registered trademark of Honeywell International, Inc. and its related companies. ©2023 Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited. Country of Origin: USA