

Phoenix G2 ATX-LITE

Station Alerting Controller



The ATX Station Controller stores the station configuration and alerting locations in memory. It can easily be configured and updated remotely through our encrypted Web interface, over a private network. The ATX computer features a secure, embedded operating system that runs on a high-speed SSD memory. It also has a touchscreen display for first responders to view station alerts.

Features

- Touchscreen display shows system status and last dispatch (and more)
- Zoned Alerting
- Voice Alert – announces dispatches without dispatcher intervention (optional)
- Four channel x 20 watt, 70 volt audio amplifier connects to existing speakers
- Heart-saver alert tone precedes all alerts
- Three Audio Inputs – Dispatch Radio, Telephone Intercom, and Auxiliary
- Two peripheral connections for use with optional Phoenix G2 Room Remotes or Message Remotes
- Support for four zones of Phoenix G2 LED Illuminated Speakers
- Support for rip-and-run network and serial printers
- Wall mount, desktop, and 19" rack install (ATX-E ordered separately)
- Simple installation – connect power, radio, Ethernet, speakers
- Remote or local configuration via web browser
- Control one MS-G series message sign, and add more as needed with Phoenix G2 Message Remotes



Technical Specifications

- Power: 750 W
- Voltage: 47-63Hz/90-132 VAC/180-264 VAC (Selectable Switch)
- Black, powder-coated steel enclosure
- Dimensions: 17.25" x 17.50" x 6.06" (WxHxL)
- 1 Year Parts & Labor Warranty
- Service Contract Available

Product Line Information

ATX-LITE. Station Alerting Controller Lite

ATX-E. Rack Mount Ears for ATX or Expansion

UPS-RM. Rack Mount UPS

UPS-STD. UPS

US Digital Designs by Honeywell

1835 E. Sixth St. Suite #27
Tempe, AZ 85281 USA
877-551-USDD
stationalerting.com

This document is not intended to be used for installation purposes. We try to keep our product information up-to-date and accurate. We cannot cover all specific applications or anticipate all requirements. All specifications are subject to change without notice. Phoenix G2® is a registered trademark of Honeywell International, Inc. and its related companies. ©2023 Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited. Country of Origin: USA